



JF12504SM



JFG416U

### Cable Capacity

20A = 16mm <sup>2</sup>
32A = 16mm <sup>2</sup>
63A = 25mm <sup>2</sup>
100A = 95mm <sup>2</sup>
125A = 95mm <sup>2</sup>
160A = 95mm <sup>2</sup>
200A = 240mm <sup>2</sup>
250A = 240mm <sup>2</sup>
315A = 240mm <sup>2</sup>
400A = 240mm <sup>2</sup>
630A = 2 x 300mm <sup>2</sup>
800A = 2 x 300mm <sup>2</sup>

### Fuse Combination Switches 20 - 800A

#### Characteristics

- Provides individual protection and control of circuits.
- Enclosures up to 100A have been designed to provide adequate cabling space without the need for additional cable spreader boxes.
- Operation of the device is through a door mounted rotary handle which is mechanically interlocked to prevent access to live conductors when the switch is in the on position. The handle is padlockable in the off position.
- All versions will accept standard BS 88 fuse links and can be converted to switch disconnector by fitting copper links.

#### Utilisation category

- AC22B - 630 - 800A
- AC23A - 20 - 630A

#### Product features

- Conforms to: BS EN 60947-3
- Rated IP31.

**Note:** Maximum rated fuse links are fitted in all fuse combination switches.

**Note:** Copper links for conversion to isolating switches

- For dimensions see page 1.67.
- For technical information see page 1.69.

Description	Cat ref.	Cat ref. Cable extension boxes if required
<b>Fuse Combination Switches Single Pole &amp; Switched Neutral</b>		
20A Fuse Combination Switch SP&SN	<b>JFB202U</b>	-
32A Fuse Combination Switch SP&SN	<b>JFB203U</b>	-
63A Fuse Combination Switch SP&SN	<b>JFD206U</b>	-
100A Fuse Combination Switch SP&SN	<b>JFE210U</b>	<b>JZA701</b>
<b>Fuse Combination Switches Triple Pole &amp; Neutral</b>		
20A Fuse Combination Switch TP&N	<b>JFB302U</b>	-
32A Fuse Combination Switch TP&N	<b>JFB303U</b>	-
63A Fuse Combination Switch TP&N	<b>JFD306U</b>	-
100A Fuse Combination Switch TP&N	<b>JFE310U</b>	<b>JZA701</b>
125A Fuse Combination Switch TP&N	<b>JFG312U</b>	<b>JZA701</b>
160A Fuse Combination Switch TP&N	<b>JFG316U</b>	<b>JZA701</b>
200A Fuse Combination Switch TP&N	<b>JFG320U</b>	<b>JZA701</b>
250A Fuse Combination Switch TP&N	<b>JFG325U</b>	<b>JZA701</b>
315A Fuse Combination Switch TP&N	<b>JFH331U</b>	<b>JZA702</b>
400A Fuse Combination Switch TP&N	<b>JFH340U</b>	<b>JZA702</b>
630A Fuse Combination Switch TP&N	<b>JFI363U</b>	<b>JZA703</b>
800A Fuse Combination Switch TP&N	<b>JFI380U</b>	<b>JZA703</b>
<b>Fuse Combination Switches Triple Pole &amp; Switched Neutral</b>		
20A Fuse Combination Switch TP&SN	<b>JFB402U</b>	-
32A Fuse Combination Switch TP&SN	<b>JFB403U</b>	-
63A Fuse Combination Switch TP&SN	<b>JFD406U</b>	-
100A Fuse Combination Switch TP&SN	<b>JFE410U</b>	<b>JZA701</b>
125A Fuse Combination Switch TP&SN	<b>JFG412U</b>	<b>JZA701</b>
160A Fuse Combination Switch TP&SN	<b>JFG416U</b>	<b>JZA701</b>
200A Fuse Combination Switch TP&SN	<b>JFG420U</b>	<b>JZA701</b>
250A Fuse Combination Switch TP&SN	<b>JFG425U</b>	<b>JZA701</b>
315A Fuse Combination Switch TP&SN	<b>JFH431U</b>	<b>JZA702</b>
400A Fuse Combination Switch TP&SN	<b>JFH440U</b>	<b>JZA702</b>
630A Fuse Combination Switch TP&SN	<b>JFI463U</b>	<b>JZA703</b>
800A Fuse Combination Switch TP&SN	<b>JFI480U</b>	<b>JZA703</b>
<b>Copper Links</b>		
63A	<b>JC60L</b>	-
100A	<b>JC10L</b>	-
125 / 200A	<b>JC20L</b>	-
315 / 400A	<b>JC40L</b>	-
630A	<b>JC63L</b>	-