




**Load table**

Products	MIN	MINs	MINp, MINt
<b>Type of lighting</b>	<b>Maximum power</b>		
230 V incandescent and halogen lamps	2300 W	2300 W	3600 W
Non-corrected / serial-corrected / dual mounted fluorescent tubes with conventional ballast	2300 VA	2300 VA	3600 VA <sup>(1)</sup>
Fluocompact lamps with conventional ballast	2000 VA	1500 VA	1500 VA <sup>(1)</sup>
Parallel-corrected fluorescent tubes with conventional ballast	1300 VA (70 F)	400 VA (42 µF)	1200 VA (120 µF) <sup>(1)</sup>
Fluorescent tubes with electronic ballast	300 VA	300 VA	1000 VA
Fluocompact lamps with electronic ballast	9 x 7 W, 6 x 11 W, 5 x 15 W, 5 x 20 W	9 x 7 W, 7 x 11 W, 7 x 15 W, 7 x 20 W, 7 x 23 W	34 x 7 W, 27 x 11 W, 24 x 15 W, 22 x 23 W

<sup>(1)</sup> The "switch-off warning" function is not available for these types of loads.

**Connection**



Type	Tightening torque	Copper cables	
		Rigid	Flexible or with ferrule
MIN, MINs, MINp, MINt	1.2 N.m	 ≤ 6 mm <sup>2</sup>	 ≤ 6 mm <sup>2</sup>