

Arteor™ lighting control and automation BUS/SCS

■ Actuators and dimmers max. loads at 230 V

		Universal								
		Leading edge				Trailing edge				
Cat.Nos		Incandescent lamp	Halogen lamp	ELV halogen with ferromagnetic transformer	ELV halogen with electronic transformer	Fluorescent tube	Compact fluorescent lamp	LED	Fluorescent lamps with 0-10 V ballast	Reducer motor for shutter
ACTUATORS	0 038 41	3500 W	3500 W	1000 VA	1000 VA	1000 VA	1000 VA			
	0 038 42	2300 W	2300 W	500 VA	250 VA	250 VA	250 VA			500 W
	0 038 44	1400 W	1400 W	500 VA	70 VA	70 VA	70 VA			500 W
	0 026 01	2 x 3600 W	2 x 3600 W	2 x 3600 VA	2 x 3600 VA	2 x 1000 VA	2 x 1000 VA	-	-	-
	0 026 02	4 x 1000 W	4 x 1000 W	4 x 500 VA	4 x 500 VA	4 x 500 VA	4 x 500 VA	4 x 500 VA		4 x 100 VA
DIMMERS	0 036 56							10 x 55 W	10 x 55 VA	
	0 026 11								1000 VA - 50 mA	
	0 026 21	1000 W	1000 W	500 VA	500 VA					
	0 026 22	2 x 500 W	2 x 500 W	2 x 250 VA	2 x 500 VA					
	0 036 52	1000 W	1000 W	1000 VA						
	0 036 53				400 VA					
0 036 65	300 W	300 W		300 VA		300 VA	300 VA			

■ Actuators and dimmers max. loads at 110 V

		Universal								
		Leading edge				Trailing edge				
Cat.Nos		Incandescent lamp	Halogen lamp	ELV halogen with ferromagnetic transformer	ELV halogen with electronic transformer	Fluorescent tube	Compact fluorescent lamp	LED	Fluorescent lamps with 0-10 V ballast	Reducer motor for shutter
ACTUATORS	0 038 41	1750 W	1750 W	500 VA	500 VA	500 VA	500 VA			
	0 038 42	1150 W	1150 W	250 VA	125 VA	125 VA	125 VA			250 W
	0 038 44	700 W	700 W	250 VA	35 VA	35 VA	35 VA			250 W
	0 026 00	1800 W	1800 W	1800 VA	1800 VA	500 VA	500 VA	-	-	-
	0 026 01	2 x 1800 W	2 x 1800 W	2 x 1800 VA	2 x 1800 VA	2 x 500 VA	2 x 500 VA	-	-	-
	0 026 02	4 x 500 W	4 x 500 W	4 x 250 VA	4 x 250 VA	4 x 250 VA	4 x 250 VA	4 x 250 VA		4 x 50 VA
DIMMERS	0 036 56									
	0 026 11								500 VA - 50 mA	
	0 026 21	500 W	500 W	250 VA	250 VA					
	0 026 22	2 x 250 W	2 x 250 W	2 x 175 VA	2 x 175 VA					
	0 036 52									
	0 036 53									
0 036 65	150 W	150 W		150 VA		150 VA	150 VA			

Installation principle, see **E-catalogue**

