

SL

making connections beautifully

| Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio | | | |
|--|--|---|--|
| 72C3XTSSB-B | | | |
| Hartland CFX Satin Brass 3 gang Multi-Way Touch Slave Controller Satin Brass/Black | | | |
| Transaria of A Sauri Brass o garig Main Vvay Tousin Slave Softwork Sauri Brass Brass | | | |
| Item Image | Wiring | Dimensions | |
| | | . | |
| | Multi-Way Wiring using Slave module(s) White the state of the state o | Hamilton Hartland Cfx | |
| | | 3XTS Multi-WayTouch Slave Controller | |
| | | 165.0 | |
| Primary Range | Hartland CFX | | |
| Insert Type | 3 gang Multi-Way Touch Slave Controller | | |
| Plate Finish | Hartland CFX Satin Brass | | |
| Insert Colour | Satin Brass/Black | | |
| EAN13 Barcode | 5017504009380 | | |
| Dimensions (Nominal) | Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm | | |
| Fixing Hole Centres | Box Fixing = 120.6mm Grid Fixing = CFX Clips | | |
| Minimum Wall Box Depth | 35mm | | |
| Wattage | The same as Touch Master or Ceiling Dimmer | | |
| Switched Poles | N/A | | |
| Current Rating | The same as Touch Master or Ceiling Dimmer | | |
| Voltage | 220/250V AC | | |
| Maximum Load | The same as Touch Master | | |
| Mains Frequency | 50Hz | | |
| IP Rating | IP2XD | | |
| Contact Gap Minimum | N/A | | |
| Terminal Capacity 1 | 2 x 1mm2 | | |
| Terminal Capacity 2 | 2 x 1.5mm2 | | |
| Earth Terminal Capacity 1 | 5 x 1mm2 | | |
| Earth Terminal Capacity 2 | 4 x 1.5mm2 | | |
| Earth Terminal Capacity 3 | 3 x 2.5mm2 | | |
| Earth Terminal Capacity 4 | 1 x 4mm2 Multi-strand | | |
| Earth Terminal Capacity 5 | 1 x 6mm2 | | |
| Product Class 1 | Face plate must be earthed | | |
| Ambient Operating Temperature | -5° to +40°C | | |
| Recommended Location | Internal Use Only | | |
| Maximum Installation Altitude | 2000m | | |
| Standard/Approval | BS EN 60669-2-1 | | |
| Additional Notes | Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When using mains voltage halogen load transformer - maximum rating is 210VA. To only be used with Touch Master Dimmers | | |



SL

making connections beautifully

| Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio | | | | |
|---|--|--|--|--|
| | 72C3XTSSB-B | | | |
| Hartland CFX Satin Brass 3 gang Multi-Way Touch Slave Controller Satin Brass/Black | | | | |
| Patents and Trademarks | CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445 | | | |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. | | |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of cartain finishes | Correct as at 16 October 2018 12:37 PM E&OE | | |

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 F: +44 (0)1179 710414 E: info@hamilton-litestat.com www.hamilton-litestat.com Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84











