## Hamilton

## making connections beautifully

| Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio       |   |   |  |
|---|---|---|--|
| 7HBC1XTSAB-B  |   |   |  |
| Hartland CFX Connaught Bronze 1 gang Multi-Way Touch Slave Controller Antique Brass/Black |   |   |  |
|   |   |   |  |
| Item Image  | Wiring  | Dimensions  |  |
|   | Multi- Way Wiring using Slave module(s)   | HARTLAND GFX<br>IXTS<br>Multi-WayTouch Slave Controller |  |
| Primary Range   | Hartland CFX  |   |  |
| Insert Type   | 1 gang Multi-Way Touch Slave Controller   |   |  |
| Plate Finish  | Hartland CFX Connaught Bronze   |   |  |
| Insert Colour   | Antique Brass/Black   |   |  |
| EAN13 Barcode   | 5017504012632   |   |  |
| Dimensions (Nominal)  | Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm  |   |  |
| Fixing Hole Centres   | Box Fixing = 60.3mm Grid Fixing = CFX Clips   |   |  |
| Minimum Wall Box Depth  | 35mm  |   |  |
| Wattage   | The same as Touch Master or Ceiling Dimmer  |   |  |
| Switched Poles  | N/A   |   |  |
| Current Rating  | The same as Touch Master or Ceiling Dimmer  |   |  |
| Voltage   | 220/250V AC   |   |  |
| Maximum Load  | The same as Touch Master  |   |  |
| Mains Frequency   | 50Hz  |   |  |
| IP Rating   | IP2XD   |   |  |
| Contact Gap Minimum   | NA  |   |  |
| Terminal Capacity 1   | 2 x 1mm2  |   |  |
| Terminal Capacity 2   | 2 x 1.5mm2  |   |  |
| Earth Terminal Capacity 1   | 5 x 1mm2  |   |  |
| Earth Terminal Capacity 2   | 4 x 1.5mm2  |   |  |
| Earth Terminal Capacity 3   | 3 x 2.5mm2  |   |  |
| Earth Terminal Capacity 4   | 1 x 4mm2 Multi-strand   |   |  |
| Earth Terminal Capacity 5   | 1 x 6mm2  |   |  |
| Product Class 1   | Face plate must be earthed  |   |  |
| Ambient Operating Temperature   | -5° to +40°C  |   |  |
| Recommended Location  | Internal Use Only   |   |  |
| Maximum Installation Altitude   | 2000m   |   |  |
| Standard/Approval   | BS EN 60669-2-1   |   |  |
| Additional Notes  | Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When using mains voltage halogen load transformer - maximum rating is 210VA. To only be used with Touch Master Dimmers |   |  |

SL

# Hamilton

### making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

#### 7HBC1XTSAB-B

#### Hartland CFX Connaught Bronze 1 gang Multi-Way Touch Slave Controller Antique Brass/Black

|   |   | •  |
|---|---|--|
| Patents and Trademarks  | CFX is a Registered Trade Mark No 2398667<br>Hartland CFX is a Registered Design under Reference Nos.<br>R21 = 3023446 SS2 =3023445         |  |
| All products listed conform to current British or<br>European standard and the product information is<br>correct at the time of going to press. | All accessories are manufactured under an accredited<br>BS EN ISO 9001 : 2015 Quality Management System.                                    | It is the policy of the company to improve products<br>as part of our development programme.<br>Therefore, we reserve the right to alter designs<br>and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within<br>the limitations of reproduction and printing<br>process and are not binding.                | Due to manufacturing processes we cannot<br>guarantee an exact colour match and shadings of<br>of certain finishes.                         | Correct as at 16 October 2018 12:41 PM<br>E&OE   |
|   | ad, Brislington, Bristol, BS4 5NZ<br>ce 1 Rushmills, Bedford Road, Northampton NN4 7YB<br>ondon No. 941624 VAT Registration No. 222 6607 84 | Listed in Minimule product selector  |

SL