




## 911XTSAB-B

### Cheriton Georgian Antique Brass 1 gang Multi-Way Touch Slave Controller Antique Brass/Black

| Item Image  | Wiring   | Dimensions  |
|---|--|---|
|  |  <p>Multi-Way Wiring using Slave module(s)</p> <p>MASTER MODULE SLAVE MODULE SLAVE MODULE<br/>ONLY ONE MASTER MODULE IS USED PER CIRCUIT.</p> |  <p>Hamilton<br/>CHERITON GEORGIAN<br/>1XTS<br/>Multi-Way Touch Slave Controller</p> |

|   |  |   |
|---|--|---|
| Primary Range   | Cheriton   |   |
| Insert Type   | 1 gang Multi-Way Touch Slave Controller  |   |
| Plate Finish  | Cheriton Georgian GRID-IT Antique Brass  |   |
| Insert Colour   | Antique Brass/Black  |   |
| EAN13 Barcode   | 5028690361428  |   |
| Dimensions (Nominal)  | Single: Height = 88.0mm Width = 88.0mm Depth = 10.5mm  |   |
| Fixing Hole Centres   | Box Fixing = 60.3mm Grid Fixing = 49.2mm   |   |
| Minimum Wall Box Depth  | 35mm   |   |
| Wattage   | The same as Touch Master or Ceiling Dimmer   |   |
| Switched Poles  | N/A  |   |
| Current Rating  | The same as Touch Master or Ceiling Dimmer   |   |
| Voltage   | 220/250V AC  |   |
| Maximum Load  | The same as Touch Master   |   |
| Mains Frequency   | 50Hz   |   |
| IP Rating   | IP2XD  |   |
| Contact Gap Minimum   | N/A  |   |
| Terminal Capacity 1   | 2 x 1mm <sup>2</sup>   |   |
| Terminal Capacity 2   | 2 x 1.5mm <sup>2</sup>   |   |
| Earth Terminal Capacity 1   | 5 x 1mm <sup>2</sup>   |   |
| Earth Terminal Capacity 2   | 4 x 1.5mm <sup>2</sup>   |   |
| Earth Terminal Capacity 3   | 3 x 2.5mm <sup>2</sup>   |   |
| Earth Terminal Capacity 4   | 1 x 4mm <sup>2</sup> Multi-strand  |   |
| Earth Terminal Capacity 5   | 1 x 6mm <sup>2</sup>   |   |
| Product Class 1   | Face plate must be earthed   |   |
| Ambient Operating Temperature   | -5° to +40°C   |   |
| Recommended Location  | Internal Use Only  |   |
| Maximum Installation Altitude   | 2000m  |   |
| Standard/Approval   | BS EN 60669-2-1  |   |
| Additional Notes  | Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltage halogen lamps- dimmers should be de-rated by 25%. When using mains voltage halogen load transformer - maximum rating is 210VA. To only be used with Touch Master Dimmers |   |
| Patents and Trademarks  | Cheriton is a Registered Trade Mark No. 2344779  |   |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.  | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.                | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.  | Correct as at 12 October 2018 04:41 PM E&OE   |

# Hamilton<sup>®</sup>

making connections beautifully

SL

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio