SL

Product Class 1

Standard/Approval

Additional Notes

Patents and Trademarks

All products listed conform to current British or

European standard and the product information is

correct at the time of going to press.

Illustrations and diagrams are reproduced within

Ambient Operating Temperature Recommended Location

Maximum Installation Altitude

Item Image

making connections beautifully

Dimensions

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

914XTSAB-B

Cheriton Georgian Antique Brass 4 gang Multi-Way Touch Slave Controller Antique Brass/Black

Wiring

Hamilton 4XTS
Multi-WayTouch Slave Controller Multi- Way Wiring using Slave module(s) Primary Range Cheriton Insert Type 4 gang Multi-Way Touch Slave Controller Plate Finish Cheriton Georgian GRID-IT Antique Brass Insert Colour Antique Brass/Black EAN13 Barcode 5028690361459 Dimensions (Nominal) Double: Height = 86.5mm Width = 146.0mm Depth = 10.5mm Fixing Hole Centres Box Fixing = 120.6mm Grid Fixing = 106.5mm Minimum Wall Box Depth 35mm Wattage The same as Touch Master or Ceiling Dimmer Switched Poles N/A Current Rating The same as Touch Master or Ceiling Dimmer 220/250V AC Voltage Maximum Load The same as Touch Master 50Hz Mains Frequency IP Rating IP2XD Contact Gap Minimum N/A Terminal Capacity 1 2 x 1mm2 Terminal Capacity 2 2 x 1.5mm2 Earth Terminal Capacity 1 5 x 1mm2 Earth Terminal Capacity 2 4 x 1.5mm2 Earth Terminal Capacity 3 3 x 2.5mm2 Earth Terminal Capacity 4 1 x 4mm2 Multi-strand Earth Terminal Capacity 5 1 x 6mm2

Face plate must be earthed

should be de-rated by 25%. used with Touch Master Dimmers

Cheriton is a Registered Trade Mark No. 2344779

All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.

-5° to +40°C

2000m

Internal Use Only

BS EN 60669-2-1

Due to manufacturing processes we cannot guarantee an exact colour match and shadings of the limitations of reproduction and printing process and are not binding. of certain finishes



Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers



When using mains voltage halogen load transformer - maximum rating is 210VA. To only be



It is the policy of the company to improve products

as part of our development programme Therefore, we reserve the right to alter designs and dimensions without prior notice.



Correct as at 12 October 2018 04:41 PM







Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio