



## LD3X40CB-CB

Linea-Duo CFX Copper Bronze Frame/Copper Bronze Front 3x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers Copper Bronze

Item Image	Wiring	Dimensions
 <p>Hamilton® LINEA DUO CFX 3X40 Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer</p> <p>145.0 86.0 4.0 28.5</p>	 <p>Dimmer Wiring Line Neutral Lamp</p> <p>Loop In Loop Out Two Way Switching Line Neutral Lamp</p> <p>Note: When using as a 2 Way Dimmer the L2 terminal is not used.</p> <p>Note: When switching from more than one position a two-way dimmer can only be used in conjunction with switches, i.e. only one dimmer per circuit.</p>	<p>Primary Range</p> <p>Linea-Duo CFX</p> <p>Insert Type</p> <p>3 gang 400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer</p> <p>Plate Finish</p> <p>Linea-Duo CFX Copper Bronze Frame/Copper Bronze</p> <p>Insert Colour</p> <p>Copper Bronze</p> <p>EAN13 Barcode</p> <p>5017504036058</p> <p>Dimensions (Nominal)</p> <p>Double: Height = 86.0mm Width = 145.0mm Depth = 4.0mm</p> <p>Fixing Hole Centres</p> <p>Box Fixing = 120.6mm Grid Fixing = CFX Clips</p> <p>Minimum Wall Box Depth</p> <p>35mm</p> <p>Wattage</p> <p>400W per gang</p> <p>Switched Poles</p> <p>Single</p> <p>Current Rating</p> <p>1.66 Amps per gang</p> <p>Voltage</p> <p>220/250V AC</p> <p>Maximum Load</p> <p>400W resistive per gang</p> <p>Mains Frequency</p> <p>50Hz</p> <p>IP Rating</p> <p>IP2XD</p> <p>Contact Gap Minimum</p> <p>N/A</p> <p>Terminal Capacity 1</p> <p>2 x 1mm<sup>2</sup></p> <p>Terminal Capacity 2</p> <p>2 x 1.5mm<sup>2</sup></p> <p>Earth Terminal Capacity 1</p> <p>5 x 1mm<sup>2</sup></p> <p>Earth Terminal Capacity 2</p> <p>4 x 1.5mm<sup>2</sup></p> <p>Earth Terminal Capacity 3</p> <p>3 x 2.5mm<sup>2</sup></p> <p>Earth Terminal Capacity 4</p> <p>1 x 4mm<sup>2</sup> Multi-strand</p> <p>Earth Terminal Capacity 5</p> <p>1 x 6mm<sup>2</sup></p> <p>Product Class 1</p> <p>Face plate must be earthed</p> <p>Ambient Operating Temperature</p> <p>-5° to +40°C</p> <p>Recommended Location</p> <p>Internal Use Only</p> <p>Maximum Installation Altitude</p> <p>2000m</p> <p>Standard/Approval</p> <p>BS EN 60669-2-1</p> <p>Additional Notes</p> <p>Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltage halogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility.</p>

## LD3X40CB-CB

### Linea-Duo CFX Copper Bronze Frame/Copper Bronze Front 3x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers Copper Bronze

<p>Patents and Trademarks</p>	<p>Linea is a Registered Trade Mark No 2398665                  CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B                  Linea-Duo CFX is a UK Registered Design Certificate No: R21 = 3021173 SS2 = 3021174</p>	
<p>All products listed conform to current British or European standard and the product information is correct at the time of going to press.</p>	<p>All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.</p>	<p>It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.</p>
<p>Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.</p>	<p>Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.</p>	<p>Correct as at 15 October 2018 08:14 AM                  E&amp;OE</p>

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ  
 T: +44 (0)1747 860088 F: +44 (0)1179 710414  
 E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB  
 Registered in London No. 941624 VAT Registration No. 222 6607 84



CERT. No. FA11138