## Hamilton

## making connections beautifully

SL

	Wiring Accessories • Circuit Protection • Sn	nart Lighting Control & Multi-room Audio	
LGX1XTEPB-PB			
Linea-Georgian CFX Polished Brass Frame/Polished Brass Front 1x250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Polished Brass			
Item Image	Wiring	Dimensions	
	Multi Way Wing using Retractive PTM Rocker Switcher The second state of the second st	ELECTRICAL CERT LINEA GEORGIAN CERT Resistive/Inductive Waining Edge Push On/Off Rotary Multi-Way Dimmer 55 55 55 55 55 55 55 55 55 5	
Primary Range	Linea-Georgian CFX		
Insert Type	1 gang 250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer		
Plate Finish	Linea-Georgian CFX Polished Brass Frame/Polished Brass		
Insert Colour	Polished Brass		
EAN13 Barcode	5017504809836		
Dimensions (Nominal)	Single: Height = 95.5mm Width = 95.5mm Depth = 4.0mm		
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm		
Wattage	250W Resistive 210VA Inductive		
Switched Poles	Single		
Current Rating	1.1 Amp		
Voltage	220/250V AC		
Maximum Load	250W Resistive 210VA Inductive Min Load 25W/25VA		
Mains Frequency	50Hz		
IP Rating	IP2XD		
Contact Gap Minimum	None		
Terminal Capacity 1	2 x 1mm2		
Terminal Capacity 2	2 x 1.5mm2		
Earth Terminal Capacity 1	5 x 1mm2		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m		
Standard/Approval Additional Notes	BS EN 60669-2-1 TRAILING EDGE TECHNOLOGY DIMMERS. Are suitable for control of both resistive and inductive loads. When used for dimming low voltage electronic halogen transformers it must be noted that the dimmer controls the primary side of the transformer. Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. When using mains voltage halogen load transformer - maximum rating is 210VA. NOTE: For multi-way switching a push to make retractive switch should be installed in the other positions. (Note:standard two way switches will not work with this product)		

# Hamilton

### making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

#### LGX1XTEPB-PB

#### Linea-Georgian CFX Polished Brass Frame/Polished Brass Front 1x250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Polished Brass

Patents and Trademarks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Georgian CFX is a UK Registered Design Certificate No. R21 = 2078674 SS2 = 2078673	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 15 October 2018 09:03 AM E&OE
	ad, Brislington, Bristol, BS4 5NZ cce 1 Rushmills, Bedford Road, Northampton NN4 7YB andron No. 441624 V/OI Reporteration NN6 222 6607 84	

SL