## Hamilton

## making connections beautifully

SL

|   | Wiring Accessories • Circuit Protection • Sma   | art Lighting Control & Multi-room Audio  |  |  |
|---|---|--|--|--|
|   | LPX2X40PB-SB  |  |  |  |
| Lines Darling CEV Delighed Brass From   |   | ling Edge Duch On Off Detery 2 Wey   |  |  |
| Linea-Perlina CFX Polished Brass Frame/Satin Brass Front 2x400W Resistive Leading Edge Push On-Off Rotary 2 Way<br>Switching Dimmers max 300W per gang Polished Brass |   |  |  |  |
| Item Image  | Wiring  | Dimensions   |  |  |
|   | Dimmer Weing<br>Umper Lange<br>Lange<br>The Network Weing<br>Dimmer Weing<br>Lange<br>Lange In Loop O.C. Two Wein Soldering<br>Umper Loop O.C. Two Wein | Electronic Construction Constru |  |  |
| Primary Range   | Linea-Perlina CFX   |  |  |  |
| Insert Type   | 2 gang 400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer max 300W per gang  |  |  |  |
| Plate Finish  | Linea-Perlina CFX Polished Brass Frame/Satin Brass  |  |  |  |
| Insert Colour   | Polished Brass  |  |  |  |
| EAN13 Barcode   | 5017504889425   |  |  |  |
| Dimensions (Nominal)  | Single: Height = 92.0mm Width = 92.0mm Depth = 4.0mm  |  |  |  |
| Fixing Hole Centres   | Box Fixing = 60.3mm Grid Fixing = CFX Clips   |  |  |  |
| Minimum Wall Box Depth  | 35mm  |  |  |  |
| Wattage   | 300W per gang   |  |  |  |
| Switched Poles  | Single  |  |  |  |
| Current Rating  | 1.25 Amps per gang  |  |  |  |
| Voltage   | 220/250V AC   |  |  |  |
| Maximum Load  | 300W resistive per gang   |  |  |  |
| Mains Frequency   | 50Hz  |  |  |  |
| IP Rating   | IP2XD   |  |  |  |
| Contact Gap Minimum   | N/A   |  |  |  |
| Terminal Capacity 1   | 2 x 1mm2  |  |  |  |
| Terminal Capacity 2   | 2 x 1.5mm2  |  |  |  |
| Earth Terminal Capacity 1   | 5 x 1mm2  |  |  |  |
| Earth Terminal Capacity 2   | 4 x 1.5mm2  |  |  |  |
| Earth Terminal Capacity 3   | 3 x 2.5mm2  |  |  |  |
| Earth Terminal Capacity 4   | 1 x 4mm2 Multi-strand   |  |  |  |
| Earth Terminal Capacity 5   | 1 x 6mm2  |  |  |  |
| Product Class 1   | Face plate must be earthed  |  |  |  |
| Ambient Operating Temperature   | -5° to +40°C  |  |  |  |
| Recommended Location  | Internal Use Only   |  |  |  |
| Maximum Installation Altitude   | 2000m   |  |  |  |
| Standard/Approval   | BS EN 60669-2-1   |  |  |  |
| Additional Notes  | Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility.   |  |  |  |

# Hamilton

### making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

### LPX2X40PB-SB

#### Linea-Perlina CFX Polished Brass Frame/Satin Brass Front 2x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers max 300W per gang Polished Brass

|   | 5 1 5 5  |  |
|---|--|--|
| Patents and Trademarks  | Linea is a Registered Trade Mark No 2398665<br>CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B<br>Linea-Perlina CFX SS2 is a UK Registered Design Certificate No. 2066588 |  |
| All products listed conform to current British or<br>European standard and the product information is<br>correct at the time of going to press. | All accessories are manufactured under an accredited<br>BS EN ISO 9001 : 2015 Quality Management System.   | It is the policy of the company to improve products<br>as part of our development programme.<br>Therefore, we reserve the right to alter designs<br>and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within<br>the limitations of reproduction and printing<br>process and are not binding.                | Due to manufacturing processes we cannot<br>guarantee an exact colour match and shadings of<br>of certain finishes.  | Correct as at 17 October 2018 08:05 AM<br>E&OE   |
|   | ad, Brislington, Bristol, BS4 5NZ<br>ice 1 Rushmills, Bedford Road, Northampton NN4 7YB<br>ondon No. 941624 VAT Registration No. 222 6607 84   | Listed in STrimble.<br>LUCKINS riba product selector   |

SL