



LSX1X40HB-HB

Linea-Scala CFX Connaught Bronze Frame/Connaught Bronze Front 1x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Connaught Bronze

Item Image	Wiring	Dimensions
 <p>Hamilton® LINEA SCALA CFX 1X40 Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer</p> <p>91.5 4.0 28.5</p>	 <p>Dimmer Wiring Line Neutral Lamp</p> <p>Loop In Loop Out Two Way Switching Line Neutral Lamp</p> <p>Note: When using as a 2-Way Dimmer the L2 terminal is not used.</p> <p>Note: When switching from more than one position a two-way dimmer can only be used in conjunction with switches, i.e. only one dimmer per circuit.</p>	<p>Primary Range</p> <p>Linea-Scala CFX</p> <p>Insert Type</p> <p>1 gang 400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer</p> <p>Plate Finish</p> <p>Linea-Scala CFX Connaught Bronze Frame/Connaught Bronze</p> <p>Insert Colour</p> <p>Connaught Bronze</p> <p>EAN13 Barcode</p> <p>5017504060336</p> <p>Dimensions (Nominal)</p> <p>Single: Height = 91.5mm Width = 91.5mm Depth = 4.0mm</p> <p>Fixing Hole Centres</p> <p>Box Fixing = 60.3mm Grid Fixing = CFX Clips</p> <p>Minimum Wall Box Depth</p> <p>35mm</p> <p>Wattage</p> <p>400W</p> <p>Switched Poles</p> <p>Single</p> <p>Current Rating</p> <p>1.66 Amp</p> <p>Voltage</p> <p>220/250V AC</p> <p>Maximum Load</p> <p>400W resistive Min Load</p> <p>Mains Frequency</p> <p>50Hz</p> <p>IP Rating</p> <p>IP2XD</p> <p>Contact Gap Minimum</p> <p>N/A</p> <p>Terminal Capacity 1</p> <p>2 x 1mm²</p> <p>Terminal Capacity 2</p> <p>2 x 1.5mm²</p> <p>Earth Terminal Capacity 1</p> <p>5 x 1mm²</p> <p>Earth Terminal Capacity 2</p> <p>4 x 1.5mm²</p> <p>Earth Terminal Capacity 3</p> <p>3 x 2.5mm²</p> <p>Earth Terminal Capacity 4</p> <p>1 x 4mm² Multi-strand</p> <p>Earth Terminal Capacity 5</p> <p>1 x 6mm²</p> <p>Product Class 1</p> <p>Face plate must be earthed</p> <p>Ambient Operating Temperature</p> <p>-5° to +40°C</p> <p>Recommended Location</p> <p>Internal Use Only</p> <p>Maximum Installation Altitude</p> <p>2000m</p> <p>Standard/Approval</p> <p>BS EN 60669-2-1</p> <p>Additional Notes</p> <p>Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltage halogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility.</p>

LSX1X40HB-HB

Linea-Scala CFX Connaught Bronze Frame/Connaught Bronze Front 1x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Connaught Bronze

Patents and Trademarks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Perlina CFX SS2 is a UK Registered Design Certificate No. 2066588	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 17 October 2018 08:31 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ
T: +44 (0)1747 860088 F: +44 (0)1179 710414
E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB
Registered in London No. 941624 VAT Registration No. 222 6607 84



Listed in Trimble
LUCKINS™



CERT. No. FA11138