Hamilton

making connections beautifully

SL

| | Wiring Accessories • Circuit Protection • Sn | nart Lighting Control & Multi-room Audio | | |
|--|---|--|--|--|
| LSX1XTEBK-BK | | | | |
| Linea-Scala CFX Black Nickel Frame/Black Nickel Front 1x250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Black Nickel | | | | |
| Item Image | Wiring | Dimensions | | |
| | Multi Way Wiring using Ritractive PTM Racker Switches Interview of the state of the switches | ELISEA SCALA CFX IXTE Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer | | |
| Primary Range | Linea-Scala CFX | | | |
| Insert Type | 1 gang 250W/210VA Resistive/Inductive Trailing Edge Push 0 | On/Off Rotary Multi-Way Dimmer | | |
| Plate Finish | Linea-Scala CFX Black Nickel Frame/Black Nickel | | | |
| Insert Colour | Black Nickel | | | |
| EAN13 Barcode | 5017504739836 | | | |
| Dimensions (Nominal) | Single: Height = 91.5mm Width = 91.5mm Depth = 4.0mm | | | |
| Fixing Hole Centres | Box Fixing = 60.3mm Grid Fixing = CFX Clips | | | |
| Minimum Wall Box Depth | 35mm | | | |
| Wattage | 250W Resistive 210VA Inductive | | | |
| Switched Poles | Single | | | |
| Current Rating | 1.1 Amp | | | |
| Voltage | 220/250V AC | | | |
| Maximum Load | 250W Resistive 210VA Inductive Min Load 25W/25VA | | | |
| Mains Frequency | 50Hz | | | |
| IP Rating | IP2XD | | | |
| Contact Gap Minimum | None | | | |
| Terminal Capacity 1 | 2 x 1mm2 | | | |
| Terminal Capacity 2 | 2 x 1.5mm2 | | | |
| Earth Terminal Capacity 1 | 5 x 1mm2 | | | |
| Earth Terminal Capacity 2 | 4 x 1.5mm2 | | | |
| Earth Terminal Capacity 3 | 3 x 2.5mm2 | | | |
| Earth Terminal Capacity 4 | 1 x 4mm2 Multi-strand | | | |
| Earth Terminal Capacity 5 | 1 x 6mm2 | | | |
| Product Class 1 | Face plate must be earthed | | | |
| Ambient Operating Temperature | -5° to +40°C | | | |
| Recommended Location | Internal Use Only | | | |
| Maximum Installation Altitude | 2000m | | | |
| Standard/Approval | BS EN 60669-2-1 | | | |
| Additional Notes | TRAILING EDGE TECHNOLOGY DIMMERS. Are suitable for control of both resistive and inductive loads. When used for dimming low voltage electronic halogen transformers it must be noted that the dimmer controls the primary side of the transformer. Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps-dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. When using mains voltage halogen load transformer - maximum rating is 210VA. NOTE: For multi-way switching a push to make retractive switch should be installed in the other positions. (Note:standard two way switches will not work with this product) | | | |

Hamilton

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

LSX1XTEBK-BK

Linea-Scala CFX Black Nickel Frame/Black Nickel Front 1x250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Black Nickel

| | - | |
|---|--|--|
| Patents and Trademarks | Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Perlina CFX SS2 is a UK Registered Design Certificate No. 2066588 | |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. | Correct as at 17 October 2018 08:31 A E&C |
| | ice 1 Rushmills, Bedford Road, Northampton NN4 7YB | |

SL