

SL

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

## LSX2X40CB-CB

Linea-Scala CFX Copper Bronze Frame/Copper Bronze Front 2x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers max 300W per gang Copper Bronze

| Item Image                    | Wiring   | Dimensions   |  |
|-------------------------------|--|--|--|
|                               | Demoner Wiring Live Proporal Loop In Loop Cut. Two Way Switching Live Proporal Loop In Loop Cut. Two Way Switching Live Proporal Loop In Loop Cut. Two Way Switching Live Proporal Loop In Loop Cut. Two Way Switching Loop In Loop In Loop Cut. Two Way Switching Loo | Hemilton LINEA SCALA CFX 2X40 Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer |  |
| Primary Range                 | Linea-Scala CFX  |  |  |
| Insert Type                   | 2 gang 400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer max 300W per gang   |  |  |
| Plate Finish                  | Linea-Scala CFX Copper Bronze Frame/Copper Bronze  |  |  |
| Insert Colour                 | Copper Bronze  |  |  |
| EAN13 Barcode                 | 5017504060664  |  |  |
| Dimensions (Nominal)          | Single: Height = 91.5mm Width = 91.5mm Depth = 4.0mm   |  |  |
| Fixing Hole Centres           | Box Fixing = 60.3mm Grid Fixing = CFX Clips  |  |  |
| Minimum Wall Box Depth        | 35mm   |  |  |
| Wattage                       | 300W per gang  |  |  |
| Switched Poles                | Single   |  |  |
| Current Rating                | 1.25 Amps per gang   |  |  |
| Voltage                       | 220/250V AC  |  |  |
| Maximum Load                  | 300W resistive per gang  |  |  |
| Mains Frequency               | 50Hz   |  |  |
| IP Rating                     | IP2XD  |  |  |
| Contact Gap Minimum           | N/A  |  |  |
| Terminal Capacity 1           | 2 x 1mm2   |  |  |
| Terminal Capacity 2           | 2 x 1.5mm2   |  |  |
| Earth Terminal Capacity 1     | 5 x 1mm2   |  |  |
| Earth Terminal Capacity 2     | 4 x 1.5mm2   |  |  |
| Earth Terminal Capacity 3     | 3 x 2.5mm2   |  |  |
| Earth Terminal Capacity 4     | 1 x 4mm2 Multi-strand  |  |  |
| Earth Terminal Capacity 5     | 1 x 6mm2   |  |  |
| Product Class 1               | Face plate must be earthed   |  |  |
| Ambient Operating Temperature | -5° to +40°C   |  |  |
| Recommended Location          | Internal Use Only  |  |  |
| Maximum Installation Altitude | 2000m  |  |  |
| Standard/Approval             | BS EN 60669-2-1  |  |  |
| Additional Notes              | Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility.  |  |  |



SL

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

## LSX2X40CB-CB

Linea-Scala CFX Copper Bronze Frame/Copper Bronze Front 2x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers max 300W per gang Copper Bronze

| Times man over per gaing copper tremes  |  |  |
|---|--|--|
| Patents and Trademarks  | Linea is a Registered Trade Mark No 2398665<br>CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B<br>Linea-Perlina CFX SS2 is a UK Registered Design Certificate No. 2066588 |  |
| All products listed conform to current British or<br>European standard and the product information is<br>correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.  | It is the policy of the company to improve products<br>as part of our development programme.  Therefore, we reserve the right to alter designs<br>and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing   | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of   | Correct as at 17 October 2018 08:32 AM<br>E&OE   |

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 F: +44 (0)1179 710414 E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









