## Hamilton

## making connections beautifully

SL

	Wiring Accessories • Circuit Protection • Sr	nart Lighting Control & Multi-room Audio	
	LSX4XTMSB-SSW		
Linoa Scala CEV Satin Brass Framo/Satin		tivo Trailing Edgo Touch Master Multi Way	
Linea-Scala CFX Satin Brass Frame/Satin Steel Front 4x250W/210VA Resistive/Inductive Trailing Edge Touch Master Multi-Way Dimmers Satin Brass/White			
Item Image	Wiring	Dimensions	
	Multi- Way Wiring using Slave module(s)	ELIDEA SCALA CFX AXTM Resistive/Inductive Trailing Edge Touch Master Multi-Way Dimmer	
Primary Range	Linea-Scala CFX		
Insert Type	4 gang 250W/210VA Resistive/Inductive Trailing Edge Touch Master Multi-Way Dimmer		
Plate Finish	Linea-Scala CFX Satin Brass Frame/Satin Steel		
Insert Colour	Satin Brass/White		
EAN13 Barcode	5017504660468		
Dimensions (Nominal)			
Fixing Hole Centres	Double: Height = 91.5mm Width = 150.5mm Depth = 4.0mm		
Minimum Wall Box Depth	Box Fixing = 120.6mm Grid Fixing = CFX Clips		
· · ·	35mm		
Wattage	250W Resistive 210VA Inductive		
Switched Poles	N/A		
Current Rating	1.1 Amps per gang		
Voltage	220/250V AC		
Maximum Load	250W Resistive per gang 210VA Inductive Min Load 25W/25VA		
Mains Frequency	50Hz		
IP Rating	IP2XD		
Contact Gap Minimum	N/A		
Terminal Capacity 1	2 x 1mm2		
Terminal Capacity 2	2 x 1.5mm2		
Earth Terminal Capacity 1	5 x 1mm2		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m		
Standard/Approval Additional Notes	BS EN 60669-2-1 TRAILING EDGE TECHNOLOGY DIMMERS. Are suitable for control of both resistive and inductive loads. When used for dimming low voltage electronic halogen transformers it must be noted that the dimmer controls the primary side of the transformer. Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. When using mains voltage halogen load transformer - maximum rating is 210VA. NOTE: For multi-way switching a push to make retractive switch should be installed in the other positions. (Note:standard two way switches will not work with this product)		

# Hamilton

### making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

#### LSX4XTMSB-SSW

Linea-Scala CFX Satin Brass Frame/Satin Steel Front 4x250W/210VA Resistive/Inductive Trailing Edge Touch Master Multi-Way Dimmers Satin Brass/White

Patents and Trademarks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Perlina CFX SS2 is a UK Registered Design Certificate No. 2066588	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 17 October 2018 08:35 AM E&OE
	ad, Brislington, Bristol, BS4 5NZ ice 1 Rushmills, Bedford Road, Northampton NN4 7YB ondon No. 941624 VAT Registration No. 222 6607 84	Listed in STrimble LUCKINS Product Product Selector

SL