Hamilton

making connections beautifully

SL

	PC1XTMPB-W			
Perception CFX Clear 1x250W/210VA Resistive/Inductive Trailing Edge Touch Master Multi-Way Dimmer Polished Brass/White				
Item Image	Wiring	Dimensions		
DUR WALLPAPER GOES HERE YO				
YOUR WALLPAPER GOES HERE UR WALLPAPER GOES HERE UR WALLPAPER GOES HERE UR WALLPAPER GOES HERE YOUR WALLPAPER OUR WALLPAPER OUR WALLPAPER YOUR WALLPAPER GOES HERE UR WALLPAPER GOES HERE YOUR WALLPAPER GOES HERE OUR WALLPAPER GOES HERE OUR WALLPAPER GOES HERE OUR WALLPAPER GOES HERE OUR WALLPAPER GOES HERE	Multi- Way Wiring using Slave module(s)	1XTM IXTM Resistive/Inductive Trailing Edge Touch Master Multi-Way Dimmer		
Primary Range	Perception CFX 1 gang 250W/210VA Resistive/Inductive Trailing Edge Touch	n Master Multi-Way Dimmer		
Plate Finish Insert Colour	Perception CFX Clear Polished Brass/White			
EAN13 Barcode Dimensions (Nominal)	5017504019266 Single: Height = 86.0mm Width = 86.0mm Depth = 4.0mm			
Fixing Hole Centres Minimum Wall Box Depth	Box Fixing = 60.3mm Grid Fixing = CFX Push 35mm			
Wattage Switched Poles	250W Resistive 210VA Inductive N/A			
Current Rating Voltage	1.1 Amp 220/250V AC			
Maximum Load Mains Frequency	250W Resistive 210VA Inductive Min Load 25W/25VA 50Hz			
IP Rating Contact Gap Minimum	IP2XD N/A			
Terminal Capacity 1 Terminal Capacity 2	2 x 1mm2 2 x 1.5mm2			
Earth Terminal Capacity 1 Earth Terminal Capacity 2	5 x 1mm2 4 x 1.5mm2			
Earth Terminal Capacity 3 Earth Terminal Capacity 4 Earth Terminal Capacity 4	3 x 2.5mm2 1 x 4mm2 Multi-strand			
Earth Terminal Capacity 5 Product Class 1	1 x 6mm2 Face plate must be earthed			
Ambient Operating Temperature Recommended Location	-5° to +40°C Internal Use Only			
Maximum Installation Altitude	2000m			
Standard/Approval Additional Notes	BS EN 60669-2-1 TRAILING EDGE TECHNOLOGY DIMMERS. Are suitable for control of both resistive and inductive loads. When used for dimming low voltage electronic halogen transformers it must be noted that the dimmer controls the primary side of the transformer. Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. When using mains voltage halogen load transformer - maximum rating is 210VA. NOTE: For multi-way switching a push to make retractive switch should be installed in the other positions. (Note:standard two way switches will not work with this product)			

Hamilton

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

PC1XTMPB-W

Perception CFX Clear 1x250W/210VA Resistive/Inductive Trailing Edge Touch Master Multi-Way Dimmer Polished Brass/White

Patents and Trademarks	Perception is a Registered Trade Mark No 2560269 CFX is a Registered Trade Mark No 2398667	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 16 October 2018 03:05 PM E&OE
	dd, Brislington, Bristol, BS4 5NZ ice 1 Rushmills, Bedford Road, Northampton NN4 7YB ondon No. 941624 VAT Registration No. 222 6607 84	Listed in Trimble product selector LUCKINS

SL