## Hamilton

## making connections beautifully

	Wiring Accessories • Circuit Protection • Sr	nart Lighting Control & Multi-room Audio
WOD1X2VBC Woods Ovolo Dark Oak 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Bright Chrome		
Woods Ovoid Dark Oak T gang 200VA Inductive Leading Edge Push On-On Rolary 2 way Switching Dimmer Bright Chrome		
Item Image	Wiring	Dimensions
		Hemilton Woods Oxolo Edge 12V Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer
	$\underbrace{\bigcup_{k \in \mathcal{O}} c \text{ Buch}}_{k \in \mathcal{O}} = \operatorname{Mark}_{k \in \mathcal{O}} = \operatorname{Mark}_{k \in \mathcal{O}} = \operatorname{Mark}_{k \in \mathcal{O}} = \operatorname{Mark}_{k \in \mathcal{O}}$ Now then setting from more that packing a face way driver can only be used in responsion with setting a driver or occur.	
Primary Range	Woods	
Insert Type	1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer	
Plate Finish	Woods Ovolo Dark Oak	
Insert Colour	Bright Chrome	
EAN13 Barcode	5017504334116 Single: Height = 88.0mm, Width = 88.0mm, Denth = 13.5mm	
Dimensions (Nominal)	Single: Height = 88.0mm Width = 88.0mm Depth = 13.5mm   Box Fixing = 60.3mm Grid Fixing = N/A	
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = N/A 35mm	
Minimum Wall Box Depth	200VA (low voltage)	
Wattage Switched Poles	Single	
Current Rating	0.8 Amp	
Voltage	220/250V AC	
Maximum Load	200VA (low voltage) Min Load 25VA	
Mains Frequency	50Hz	
IP Rating	IP2XD	
Contact Gap Minimum	None	
Terminal Capacity 1	2 x 1mm2	
Terminal Capacity 2	2 x 1.5mm2	
Earth Terminal Capacity 1	5 x 1mm2	
Earth Terminal Capacity 2	4 x 1.5mm2	
Earth Terminal Capacity 3	3 x 2.5mm2	
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand	
Earth Terminal Capacity 5	1 x 6mm2	
Product Class 1	Face plate must be earthed	
Ambient Operating Temperature	-5° to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS EN 60669-1	
Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE: It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 17 October 2018 12:06 PM E&OE
	ad, Brislington, Bristol, BS4 5NZ fice 1 Rushmills, Bedford Road, Northampton NN4 7YB London No. 941624 VAT Registration No. 222 6607 84	Listed in STrimble LUCKINS ridector Selector

SL