

Fire Alarm Control Panel Mains Keyswitch

Part No. **BF319**



Overview

A high-quality lockable double pole Fire Alarm Control Panel Mains Keyswitch.

Allows the Mains supply to a fire alarm panel to be switched on or off in accordance with BS 5839-1.

Ideal for use during routine test and maintenance (e.g. battery test, main board replacement etc). Note, if working on the Mains in the panel you must also follow correct practice and isolate the Mains supply at the distribution board.

Fits on a standard UK 47mm flush or surface mount back box.

Supplied with 2 x M3.5 25mm fixing screws.

BS EN60669-1 compliant.

Always read the full installation and operating instructions supplied with the unit before use.

Technical Specifications

| | |
|----------------------------------|---|
| Approvals/certifications | Compliant with BS EN60669-1 (Switches for household and similar fixed-electrical installations, General Requirements) |
| Type | Double pole, lockable. 20AX, 250V, 50/60Hz. |
| Connections | L1 and N1 IN; L2 and N2 OUT. |
| Product dimensions (mm) | 87 W x 87 H x 44 D mm (Can be mounted on a standard UK 47mm single gang flush or surface back box). |
| Construction & finish | White moulded polycarbonate. |
| IP Rating | IP20. |
| Weight | 150g. |
| Operating conditions/temperature | -10°C to +60°C. |
| Notes | When the BF319 is in the off position, you can safely perform routine maintenance tasks at the fire panel (battery test, main board replacement etc). To work on the Mains in the panel you MUST also isolate the Mains supply at the distribution board. |



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom