

# Dual 200m2 Hearing Loop Amplifier for Phased Array Loops

Part No. **DLR5**



## Overview

A dual induction loop amplifier designed to simplify the installation of a 'phased array' induction loop system in areas up to 200m2.

Includes two PDA Pro-Range induction loop amplifiers, an APPS Phase Shifter and two outreach plates providing one XLR mic and one dual phono line input.

Supplied in a 4U enclosure

Ideal for use in high-profile professional AFILS applications where minimal overspill and consistent loop coverage (i.e. no dead spots) is essential.

Adjustable level controls for all inputs.

Metal compensation.

## Technical Specifications

|                                  |   |
|----------------------------------|---|
| Type                             | Free-standing. Plugtop IEC mains lead supplied.               |
| Coverage                         | 200m2 approx.   |
| Mains supply                     | Plugtop IEC mains lead supplied.                              |
| Max battery size and type        | n/a.  |
| Auxiliary inputs                 | 1 x XLR mic (via APXM plate); 1 x dual phono (via APL plate). |
| Indicators                       | See DLR short form setup guide in Documentation section.      |
| Controls                         | See DLR short form setup guide in Documentation section.      |
| Product dimensions (mm)          | W 600 x H 270 x D 400 mm.                                     |
| Construction & finish            | Mild steel, black; blue/black label.                          |
| IP Rating                        | IP20.   |
| Weight                           | 17kg.   |
| Operating conditions/temperature | -5°C to +40°C. Max relative humidity: 95%.                    |



T 01942 322744 E sales@c-tec.co.uk  
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom