Hamilton

making connections beautifully

SL

	821X2V	
Sheer Satin Brass 1 gang 200\/A	Inductive Leading Edge Push On-Off Rotary 2	Way Switching Dimmer Satin Brass
Sheel Satin Diass 1 gang 2007A		Way Switching Diminer Satin Drass
Item Image	Wiring	Dimensions
		Hemilton SHEER 1X2V Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer
	None None NUM UN UN UN UN<	
Primary Range	Sheer	
nsert Type	1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer	
Plate Finish	Sheer Box Satin Brass	
nsert Colour	Satin Brass	
EAN13 Barcode	5017503049110	
	Single: Height = 86.0mm Width = 86.0mm Depth = 1.5mm	
Dimensions (Nominal)	Box Fixing = 60.3 mm Grid Fixing = N/A	
ixing Hole Centres	35mm	
Ainimum Wall Box Depth	200VA (low voltage)	
Vattage		
Switched Poles	Single	
Current Rating	0.8 Amp 220/250V AC	
/oltage		
Aaximum Load	200VA (low voltage) Min Load 25VA	
Aains Frequency	50Hz	
P Rating	IP2XD	
Contact Gap Minimum	None	
erminal Capacity 1	2 x 1mm2	
erminal Capacity 2	2 x 1.5mm2	
arth Terminal Capacity 1	5 x 1mm2	
arth Terminal Capacity 2	4 x 1.5mm2	
arth Terminal Capacity 3	3 x 2.5mm2	
arth Terminal Capacity 4	1 x 4mm2 Multi-strand	
arth Terminal Capacity 5	1 x 6mm2	
roduct Class 1	Face plate must be earthed	
mbient Operating Temperature	-5° to +40°C	
ecommended Location	Internal Use Only	
laximum Installation Altitude	2000m	
tandard/Approval	BS EN 60669-1	
dditional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low or dimming LED lamps de-rated by 75% - please contact our Tec the manufacturer of the transformer to confirm that it is dimmal	hnical for compatibility. NOTE: It is recommended to conta
Patents and Trademarks	Sheer is a Registered Trade Mark No. 2296586	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 17 October 2018 09:57 E&

Hamilton

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio