SL

making connections beautifully


Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

82DUS2W

Sheer Floor Satin Brass 1 gang 2A Unswitched Socket White

Item Image Wiring





		85.5
Primary Range	Sheer Floor Sockets	
Insert Type	1 gang 2A Unswitched Socket	
Plate Finish	Sheer Floor Box Satin Brass	
Insert Colour	White	
EAN13 Barcode	5017504034726	
Dimensions (Nominal)	Single: Height = 93.5mm Width = 85.5mm Depth = 3.0mm (6.5mm Hinged Cover)	
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = N/A	
Minimum Wall Box Depth	35mm	
Switched Poles	None	
Current Rating	2 Amp	
Voltage	220/250V AC	
Maximum Load	2 Amp	
Mains Frequency	50Hz	
IP Rating	IP2XD	
Contact Gap Minimum	None	
Terminal Capacity 1	5 x 1mm2	
Terminal Capacity 2	4 x 1.5mm2	
Terminal Capacity 3	2 x 2.5mm2	
Terminal Capacity 4	1 x 4mm2	
Earth Terminal Capacity 1	5 x 1mm2	
Earth Terminal Capacity 2	4 x 1.5mm2	
Earth Terminal Capacity 3	2 x 2.5mm2	
Earth Terminal Capacity 4	1 x 4mm2	
Product Class 1	Must be earthed	
Ambient Operating Temperature	-5° to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS 546	
Additional Notes	Shuttered: Yes	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.

Due to manufacturing processes we cannot

guarantee an exact colour match and shadings of

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 F: +44 (0)1179 710414
E: info@hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84











Correct as at 17 October 2018 11:27 AM



E&OE

Illustrations and diagrams are reproduced within

the limitations of reproduction and printing

process and are not binding.