

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

8CBC1X2V

Sheer CFX Copper Bronze 1 gang 200VA	Inductive Leading Edge Push On-Off Rotar	y 2 Way Switching Dimmer Copper Bronze
Item Image	Wiring	Dimensions
	LOOF IN LOOP OUT TWO WAY SMITCHISC NAME OF THE CONTROL OF TWO DAY SMITCHISC NOTIFICATION OF TWO DAY SMITCHISC LOOF IN LOOP OUT TWO DAY SMITCHISC NOTIFICATION OF TWO DAY SMITCHISC LOOF IN LOOP OUT TWO DAY SMITCHISC LOOP IN LOOP OUT TWO DAY SMITCHISC LOOP IN LOOP OUT TWO DAY SMITCHISC LOOP O	Hemilton SHEER CFX 1829 Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer
Primary Range	Sheer CFX - Designed to fit Folded Metal Wall Box Enclosure	es that comply with BS4662-2006.
Insert Type	1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer	
Plate Finish	Sheer CFX Copper Bronze	
Insert Colour	Copper Bronze	
EAN13 Barcode	5017504026592	
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 1.5mm plate + 3.0mm gasket	
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips	
Minimum Wall Box Depth	35mm	
Wattage	200VA (low voltage)	
Switched Poles	Single	
Current Rating	0.8 Amp	
Voltage	220/250V AC	
Maximum Load	200VA (low voltage) Min Load 25VA	
Mains Frequency	50Hz	
IP Rating	IP2XD	
Contact Gap Minimum	None	
Terminal Capacity 1	2 x 1mm2	
Terminal Capacity 2	2 x 1.5mm2	
Earth Terminal Capacity 1	5 x 1mm2	
Earth Terminal Capacity 2	4 x 1.5mm2	
Earth Terminal Capacity 3	3 x 2.5mm2	
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand	
Earth Terminal Capacity 5	1 x 6mm2	
Product Class 1	Face plate must be earthed	
Ambient Operating Temperature	-5° to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS EN 60669-1	
Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE:It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.	
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Trade Mark No. 2296586 Sheer CFX is a Registered Design under Reference Nos. R21 = 3020754 SS2 = 3020755	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 17 October 2018 10:43 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)179 710414 Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB E: info@hamilton-litestat.com www.hamilton-litestat.com Registered in London No. 941624 VAT Registration No. 222 6607 84















Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio