

SL

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

8RBC1X2V

Sheer CFX Richmond Bronze 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Richmond Bronze

Item Image	Wiring	Dimensions	
	LOOP IN LOOP OUT TWO INVESTIGNING MICHIGAN TO SEE THE WAY LIVE LOOP IN LOOP OUT TWO INVESTIGNING MICHIGAN TO SEE THE WAY LOOP IN LOOP OUT TWO INVESTIGNING LOOP OUT	Hamilton SHEER CFX 1129 Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer	
Primary Range	Sheer CFX - Designed to fit Folded Metal Wall Box Enclosures that comply with BS4662-2006.		
Insert Type	1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer		
Plate Finish	Sheer CFX Richmond Bronze		
Insert Colour	Richmond Bronze		
EAN13 Barcode	5017504029647		
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 1.5mm plate + 3.0mm gasket		
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm		
Wattage	200VA (low voltage)		
Switched Poles	Single		
Current Rating	0.8 Amp		
Voltage	220/250V AC		
Maximum Load	200VA (low voltage) Min Load 25VA		
Mains Frequency	50Hz		
IP Rating	IP2XD		
Contact Gap Minimum	None		
Terminal Capacity 1	2 x 1mm2		
Terminal Capacity 2	2 x 1.5mm2		
Earth Terminal Capacity 1	5 x 1mm2		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m		
Standard/Approval	BS EN 60669-1		
Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE:It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.		



SL

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

8RBC1X2V

Sheer CFX Richmond Bronze 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Richmond

Biolize		
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Trade Mark No. 2296586 Sheer CFX is a Registered Design under Reference Nos. R21 = 3020754 SS2 = 3020755	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of	Correct as at 17 October 2018 10:45 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 F: +44 (0)1179 710414 E: info@hamilton-litestat.com www.hamilton-litestat.com Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









