Hamilto

making connections beautifully

SL

Voltage

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio 931XTE Cheriton Victorian Antique Brass 1x250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer **Antique Brass** Item Image Wiring Dimensions Hamilton CHERITON VICTORIAN 1XTE Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer 60.3 Primary Range Cheriton Insert Type 1 gang 250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Cheriton Victorian Box Antique Brass Plate Finish Insert Colour Antique Brass EAN13 Barcode 5028690389330 Dimensions (Nominal) Single: Height = 88.5mm Width = 88.5mm Depth = 7.5mm **Fixing Hole Centres** Box Fixing = 60.3mm Grid Fixing = N/A Minimum Wall Box Depth 35mm Wattage 250W Resistive 210VA Inductive Switched Poles Single Current Rating 1.1 Amp 220/250V AC 250W Resistive 210VA Inductive Min Load 25W/25VA Maximum Load Mains Frequency 50Hz IP Rating IP2XD Contact Gap Minimum None Terminal Capacity 1 2 x 1mm2 **Terminal Capacity 2** 2 x 1.5mm2 Earth Terminal Capacity 1 5 x 1mm2 Earth Terminal Capacity 2 4 x 1.5mm2 Earth Terminal Capacity 3 3 x 2.5mm2 Earth Terminal Capacity 4 1 x 4mm2 Multi-strand Earth Terminal Capacity 5 1 x 6mm2 Product Class 1 Face plate must be earthed Ambient Operating Temperature -5° to +40°C Internal Use Only **Recommended Location** Maximum Installation Altitude 2000m Standard/Approval BS EN 60669-2-1 TRAILING EDGE TECHNOLOGY DIMMERS. Are suitable for control of both resistive and inductive loads. When used for dimming low voltage electronic halogen transformers it must be noted that the dimmer controls the primary side of the transformer. Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lampsdimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for Additional Notes compatibility. When using mains voltage halogen load transformer - maximum rating is 210VA. NOTE: For multi-way switching a push to make retractive switch should be installed in the other positions. (Note:standard two way switches will not work with this product) 931XTE - Cheriton Victorian Antique Brass 1x250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Antique Brass

Hamilton

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

<u>931XTE</u>

Cheriton Victorian Antique Brass 1x250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Antique Brass

Patents and Trademarks	Cheriton is a Registered Trade Mark No. 2344779			
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.		It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.	
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.		Correct as at 12 October 2018 04:42 PM E&OE	
	d, Brislington, Bristol, BS4 5NZ ice 1 Rushmills, Bedford Road, Northampton NN4 7YB ondon No. 941624 VAT Registration No. 222 6607 84		Listed in Trimble	riba product selector

SL