SL

## making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

## **IDPFGBL-B**

Grid-IT 20AX Double Pole Rocker Module Fridge Black/Black

Wiring



Item Image



**Dimensions** 

Primary Range	GRID-IT	
Insert Type	20AX Double Pole Rocker Module + Printed Legend	
Plate Finish	GRID-IT Module No Plate Colour	
Insert Colour	Black/Black	
EAN13 Barcode	5017504070458	
Weight	43 GR	
Switched Poles	Double	
Current Rating	20AX	
Voltage	220/250V AC	
Maximum Load	20 Amp inductive	
Mains Frequency	50Hz	
IP Rating	IP2XD	
Contact Gap Minimum	3mm	
Terminal Capacity 1	5 x 1mm2	
Terminal Capacity 2	4 x 1.5mm2	
Terminal Capacity 3	2 x 2.5mm2	
Terminal Capacity 4	1 x 4mm2 Multi-strand	
Terminal Capacity 5	1 x 6mm2	
Earth Terminal Capacity 1	6 x 1mm2	
Earth Terminal Capacity 2	5 x 1.5mm2	
Earth Terminal Capacity 3	3 x 2.5mm2	
Earth Terminal Capacity 4	2 x 4mm2 Multi-strand	
Earth Terminal Capacity 5	1 x 6mm2	
Product Class 1	Face plate must be earthed	
Ambient Operating Temperature	-5° to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS EN 60669-1	
Module Size	Height = 51mm Width = 23mm Depth = 21mm	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme.  Therefore, we reserve the right to alter designs and dimensions without prior notice.

Due to manufacturing processes we cannot

guarantee an exact colour match and shadings of

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 F: +44 (0)1179 710414 E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









Correct as at 15 October 2018 09:54 AM



Illustrations and diagrams are reproduced within

the limitations of reproduction and printing

process and are not binding.