SL

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

IR212SC-B

Grid-IT 20AX 2 Way Rocker Module Satin Chrome/Black Item Image Wiring **Dimensions** GRID-IT Primary Range Insert Type 20AX 2 Way Rocker Module Plate Finish GRID-IT Module No Plate Colour Insert Colour Satin Chrome/Black EAN13 Barcode 5051164119614 Weight 43 GR Switched Poles Single **Current Rating** 20AX Voltage 220/250V AC Maximum Load 20 Amp inductive Mains Frequency 50Hz IP Rating IP2XD Contact Gap Minimum 3mm Terminal Capacity 1 5 x 1mm2 Terminal Capacity 2 4 x 1.5mm2 **Terminal Capacity 3** 2 x 2 5mm2 Terminal Capacity 4 2 x 4mm2 Multi-strand **Terminal Capacity 5** 1 x 6mm2 Earth Terminal Capacity 1 6 x 1mm2 Earth Terminal Capacity 2 5 x 1.5mm2 Earth Terminal Capacity 3 3 x 2.5mm2 Earth Terminal Capacity 4 2 x 4mm2 Multi-strand Earth Terminal Capacity 5 1 x 6mm2 Product Class 1 Face plate must be earthed -5° to +40°C **Ambient Operating Temperature** Recommended Location Internal Use Only Maximum Installation Altitude 2000m Standard/Approval BS EN 60669-1 Module Size Height = 51mm Width = 23mm Depth = 21mm All products listed conform to current British or All accessories are manufactured under an accredited It is the policy of the company to improve products European standard and the product information is BS EN ISO 9001: 2015 Quality Management System. as part of our development programme Therefore, we reserve the right to alter designs correct at the time of going to press. and dimensions without prior notice.

Due to manufacturing processes we cannot

guarantee an exact colour match and shadings of

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 F: +44 (0)1179 710414 E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









Correct as at 15 October 2018 09:55 AM



E&OE

Illustrations and diagrams are reproduced within

the limitations of reproduction and printing

process and are not binding.