Hamilton

SL	making connections beautifully			
에 잘 안에서 전성에 보는 것이는 것이 많아?	Wiring Accessories • Circuit Protection • Sm	art Lighting Control & Multi-room Audio		
LD1X2VRB-RB Linea-Duo CFX Richmond Bronze Frame/Richmond Bronze Front 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Richmond Bronze				
Item Image	Wiring	Dimensions		
		Hamilton LINE DUO CFX 122V Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer		
	Name NUTRITION LOC UC UC </td <td></td>			
Primary Range	Linea-Duo CFX			
Insert Type	1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer			
Plate Finish	Linea-Duo CFX Richmond Bronze Frame/Richmond Bronze			
Insert Colour	Richmond Bronze			
EAN13 Barcode	5017504035402			
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 4.0mm			
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips			
Minimum Wall Box Depth	35mm			
Wattage	200VA (low voltage)			
Switched Poles	Single			
Current Rating	0.8 Amp			
Voltage	220/250V AC			
Maximum Load	200VA (low voltage) Min Load 25VA 50Hz			
Mains Frequency	IP2XD			
IP Rating Contact Gap Minimum	None			
Terminal Capacity 1	2 x 1mm2			
Terminal Capacity 2	2 x 1.5mm2			
Earth Terminal Capacity 1	5 x 1mm2			
Earth Terminal Capacity 2	4 x 1.5mm2			
Earth Terminal Capacity 3	3 x 2.5mm2			
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand			
Earth Terminal Capacity 5	1 x 6mm2			
Product Class 1	Face plate must be earthed			
Ambient Operating Temperature	-5° to +40°C			
Recommended Location	Internal Use Only			
Maximum Installation Altitude	2000m			
Standard/Approval	BS EN 60669-1			
Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE: It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.			

Hamilton

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

LD1X2VRB-RB

Linea-Duo CFX Richmond Bronze Frame/Richmond Bronze Front 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Richmond Bronze

	, ,	
Patents and Trademarks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Duo CFX is a UK Registered Design Certificate No: R21 = 3021173 SS2 = 3021174	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 15 October 2018 08:12 AM E&OE
	Ad, Brislington, Bristol, BS4 5NZ ice 1 Rushmills, Bedford Road, Northampton NN4 7YB ondon No. 941624 VAT Registration No. 222 6607 84	Listed in & Trimble product selector

SL