## Hamilton

## making connections beautifully

SL

	Wining Accessories + Circuit Protection + Sn	nart Lighting Control & Multi more Audio
Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio		
LDR322BC-BSW		
Linea-Duo CFX Bright Chrome Frame/Bright Steel Front 2 gang 20AX Intermediate Rocker Bright Chrome/White		
Item Image	Wiring	Dimensions
	2 Way Switch Switch 2 Way Switch 2 Way Switch 2 Way Switch 2 Way Switch 2 Way Switch 2 Uay Switch 2 Uay Switch 2 Uay Switch 1 0 1 1 0 1 0 1 0 1 0 1 0 1 0 1 0 1 0 1	HEIDELOUS CFX R322 Intermediate Rocker
Primary Range		
Insert Type	2 gang 20AX Intermediate Rocker	
Plate Finish	Linea-Duo CFX Bright Chrome Frame/Bright Steel	
Insert Colour	Bright Chrome/White	
EAN13 Barcode	5017504207359	
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 4.0mm	
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips	
Minimum Wall Box Depth	35mm	
Switched Poles	Single	
Current Rating	20AX 220/250V AC	
Voltage	220/250V AC	
Maximum Load	20 Amp inductive	
Mains Frequency IP Rating	50Hz IP2XD	
Contact Gap Minimum	3mm	
Terminal Capacity 1	5 x 1mm2	
Terminal Capacity 2	4 x 1.5mm2	
Terminal Capacity 3	2 x 2.5mm2	
Terminal Capacity 4	2 x 4mm2 Multi-strand	
Terminal Capacity 5	1 x 6mm2	
Earth Terminal Capacity 1	6 x 1mm2	
Earth Terminal Capacity 2	5 x 1.5mm2	
Earth Terminal Capacity 3	3 x 2.5mm2	
Earth Terminal Capacity 4	2 x 4mm2 Multi-strand	
Earth Terminal Capacity 5	1 x 6mm2	
Product Class 1	Must be earthed	
Ambient Operating Temperature	-5° to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS EN 60669-1	
Patents and Trademarks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Duo CFX is a UK Registered Design Certificate No: R21 = 3021173 SS2 = 3021174	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 15 October 2018 08:21 AM E&OE
R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ T: +44 (0)1747 860088 F: +44 (0)179 710414 E: info@hamilton-litestat.com www.hamilton-litestat.com Registered office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered office 1 Rushmills, Bedford Road, Northampton NN4 7YB Rushmills, Bedford Road, Northampton NN4 7		

LDR322BC-BSW - Linea-Duo CFX Bright Chrome Frame/Bright Steel Front 2 gang 20AX Intermediate Rocker Bright Chrome/White

Hamilton

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio