Hamilton

making connections beautifully

SL

	Wiring Accessories • Circuit Protection • Sn	nart Lighting Control & Multi-room Audio	
	LGX1X2VRB-RB		
Linea-Georgian CEX Richmond Bronze	Frame/Richmond Bronze Front 1 gang 200\	/A Inductive Leading Edge Push On-Off	
Rot	ary 2 Way Switching Dimmer Richmond Bro	nze	
Item Image	Wiring	Dimensions	
-			
		1X2V Inductive Leading Edge Push On-Off Rotary	
		2 Way Switching Dimmer	
	LOO IN LOOP OUT TWO WAY SWITCHING LOOP IN LOOP OUT TWO WAY SWITCHING MEUTRAL MEUTRAL 10000 MEUTRAL 100000 100000 100000 10000 10000 10000 100000 100000 1000	95.5	
	OL1 Two Way DL2 Two Way Tensor		
	Note: When and the position a two way dimmer can only be used in conjunction with switches		
	Au, Unity only entitled per croux.		
		- C	
Primary Range	Linea-Georgian CFX		
Insert Type	1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer		
Plate Finish	Linea-Georgian CFX Richmond Bronze Frame/Richmond Bronze		
Insert Colour	Richmond Bronze		
EAN13 Barcode	5017504042752		
Dimensions (Nominal)	Single: Height = 95.5mm Width = 95.5mm Depth = 4.0mm		
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm		
Wattage	200VA (low voltage)		
Switched Poles	Single		
Current Rating	0.8 Amp		
Voltage	220/250V AC		
Maximum Load	200VA (low voltage) Min Load 25VA		
Mains Frequency	50Hz		
IP Rating	IP2XD		
Contact Gap Minimum	None		
Terminal Capacity 1	2 x 1mm2		
Terminal Capacity 2	2 x 1.5mm2		
Earth Terminal Capacity 1	5 x 1mm2		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m		
Standard/Approval	BS EN 60669-1		
Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE: It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.		

Hamilton

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

LGX1X2VRB-RB

Linea-Georgian CFX Richmond Bronze Frame/Richmond Bronze Front 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Richmond Bronze

Patents and Trademarks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Georgian CFX is a UK Registered Design Certificate No. R21 = 2078674 SS2 = 2078673		
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accree BS EN ISO 9001 : 2015 Quality Management Sys		It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes.		Correct as at 15 October 2018 09:03 A E&C
	ad, Brislington, Bristol, BS4 5NZ ice 1 Rushmills, Bedford Road, Northampton NN4 7YB ondon No. 941624 VAT Registration No. 222 6607 84		Listed in Trimble product selector

SL