## Hamilton

## making connections beautifully

SL

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio				
LPX1X2VCB-CB				
Linea-Perlina CFX Copper Bronze Frame/Copper Bronze Front 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Copper Bronze				
Item Image	Wiring	Dimensions		
	Logr is Logr Oct TNO WAY SIRTCHING NUT WAY LOGR IS LOGP OLT TNO BAY SIRTCHING NUT WAY LOGR IS LOGP OLT TNO BAY SIRTCHING ILOGR IS LOGP OLT TNO BAY SIRTCHING ILOGP	Electric CFX LINEA PERLINA CFX 1X2V Inductive Leading Edge Push On-Off Rotary 2Way Switching Dimmer 20 20 20 20 20 20 20 20 20 20		
Primary Range	Linea-Perlina CFX			
Insert Type	1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer			
Plate Finish	Linea-Perlina CFX Copper Bronze Frame/Copper Bronze			
Insert Colour	Copper Bronze			
EAN13 Barcode	5017504048501			
Dimensions (Nominal)	Single: Height = 92.0mm Width = 92.0mm Depth = 4.0mm			
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips			
Minimum Wall Box Depth	35mm			
Wattage	200VA (low voltage)			
Switched Poles	Single			
Current Rating	0.8 Amp			
Voltage	220/250V AC			
Maximum Load	200VA (low voltage) Min Load 25VA			
Mains Frequency	50Hz			
IP Rating	IP2XD			
Contact Gap Minimum	None			
Terminal Capacity 1	2 x 1mm2			
Terminal Capacity 2	2 x 1.5mm2			
Earth Terminal Capacity 1	5 x 1mm2			
Earth Terminal Capacity 2	4 x 1.5mm2			
Earth Terminal Capacity 3	3 x 2.5mm2			
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand			
Earth Terminal Capacity 5	1 x 6mm2			
Product Class 1	Face plate must be earthed			
Ambient Operating Temperature	-5° to +40°C			
Recommended Location	Internal Use Only			
Maximum Installation Altitude	2000m			
Standard/Approval	BS EN 60669-1			
Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE: It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.			

# Hamilton

### making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

#### LPX1X2VCB-CB

#### Linea-Perlina CFX Copper Bronze Frame/Copper Bronze Front 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Copper Bronze

Patents and Trademarks	CFX is a Registered Trade Mark No 239866	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Perlina CFX SS2 is a UK Registered Design Certificate No. 2066588		
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an BS EN ISO 9001 : 2015 Quality Managemen		It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.	
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we ca guarantee an exact colour match and sha of certain finishes.		Correct as at 17 October 2018 08:04 AM E&OI	
	ville Road, Brislington, Bristol, BS4 5NZ tered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB tered in London No. 941624 VAT Registration No. 222 6607 84		Listed in STrimble LUCKINS riba product selector	

SL