Hamilton

making connections beautifully

SL

	J	
	Wiring Accessories • Circuit Protection • Sr	nar t Egnung Control & Pluiti-room Audio
LSXR31BC-BKB		
Linea-Scala CFX Bright Chrome Frame/Black Nickel Front 1 gang 10AX Intermediate Rocker Bright Chrome/Black		
Item Image	Wiring	Dimensions
	2 Way Switch Switch 2 Way Switch 2 Way Switch 2 Way Switch 2 Way Switch 10 10 10 10 10 10 10 10 10 10	HEIDELINEA SCALA CFX R31 Intermediate Rocker
Primary Range	Linea-Scala CFX	
Insert Type	1 gang 10AX Intermediate Rocker	
Plate Finish	Linea-Scala CFX Bright Chrome Frame/Black Nickel	
Insert Colour	Bright Chrome/Black	
EAN13 Barcode	5017504592318	
Dimensions (Nominal)	Single: Height = 91.5mm Width = 91.5mm Depth = 4.0mm	
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips	
Minimum Wall Box Depth	25mm	
Switched Poles	Single	
Current Rating	10AX	
Voltage	220/250V AC	
Maximum Load	10 Amp inductive	
Mains Frequency	50Hz	
IP Rating	IP2XD	
Contact Gap Minimum	3mm	
Terminal Capacity 1	5 x 1mm2	
Terminal Capacity 2	4 x 1.5mm2	
Terminal Capacity 3	1 x 2.5mm2	
Terminal Capacity 4	1 x 4mm2 Multi-strand	
Terminal Capacity 5	1 x 6mm2	
Earth Terminal Capacity 1	5 x 1mm2	
Earth Terminal Capacity 2	4 x 1.5mm2	
Earth Terminal Capacity 3	3 x 2.5mm2	
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand	
Earth Terminal Capacity 5	1 x 6mm2	
Product Class 1	Must be earthed	
Ambient Operating Temperature	-5° to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS EN 60669-1	
Patents and Trademarks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Linea-Perlina CFX SS2 is a UK Registered Design Certificate No. 2066588	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 17 October 2018 08:40 AM E&OE
R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ T: +44 (0)1747 860088 F: +44 (0)1179 710414 E: info@hamilton-litestat.com www.hamilton-litestat.com www.hamilton-litestat		

LSXR31BC-BKB - Linea-Scala CFX Bright Chrome Frame/Black Nickel Front 1 gang 10AX Intermediate Rocker Bright Chrome/Black

Hamilton

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio