










Actuators and dimmers max. loads at 230 V

											
Cat. Nos.	Installation factor	Incandescent lamp Halogen lamp	ELV halogen with ferromagnetic transformer	ELV halogen with electronic transformer	Fluorescent tube lamp	Compact fluorescent lamp	LED lamps	Lamps with 0-10 V ballast	Lamps with DALI ballast	Motors	
ACTUATORS	F411U2	2 DIN	2 x 2300 W	2 x 920 VA	2 x 920 VA	2 x 920 W	2 x 500 W	2 x 500 W	-	-	1 x 460 W
	F411/4	2 DIN	4 x 460 W	4 x 460 VA	4 x 70 VA	4 x 70 W	4 x 70 W max 2 lamps	4 x 70 VA max 2 lamps	-	-	2 x 460 W
	F411/1NC	2 DIN	1 x 2300 W	1 x 920 VA	1 x 920 W	1 x 920 W	1 x 500 W max 10 lamps	1 x 500 W max 10 lamps	-	-	-
	F401	2 DIN	-	-	-	-	-	-	-	-	1 x 460 W
	3476	-	1 x 460W	1 x 460 VA	-	-	1 x 40 W (1 lamp)	1 x 40 W (1 lamp)	-	-	-
DIMMERS	F413N	2 DIN	-	-	-	-	-	1 x 460 W ballast type T5, T8, compact or driver for LED	-	-	-
	BMDI1002	10 DIN	-	-	-	-	-	4 x 1000 VA	-	-	-
	0026 33	6 DIN	-	-	-	-	-	-	8 x 16 ballasts	-	-
	F461U1	6 DIN	1 x 1000 W	1 x 1000 VA	1 x 1000 VA	-	-	-	-	-	-
	F418U2	4 DIN	2 x 300 W 1 x 600 W	2 x 300 VA 1 x 600 VA	2 x 300 VA 1 x 600 VA	-	2 x 300 VA 1 x 600 VA	2 x 300 VA 1 x 600 VA	-	-	-