




71C2J12B

Hartland CFX Polished Brass 2 gang RJ12 Outlet - Unshielded Black

Item Image	Wiring	Dimensions																																													
	 <table border="1" data-bbox="808 646 967 730"> <thead> <tr> <th>RIGHT</th> <th>LEFT</th> <th>Wiring Colour Codes</th> <th>SOFT WIRE</th> <th>SOFT WIRE</th> </tr> </thead> <tbody> <tr> <td>1</td> <td>1</td> <td>NOT USED</td> <td>NOT USED</td> <td></td> </tr> <tr> <td>2</td> <td>2</td> <td>GREEN / White</td> <td>BLUE</td> <td></td> </tr> <tr> <td>3</td> <td>3</td> <td>ORANGE / White</td> <td>YELLOW</td> <td></td> </tr> <tr> <td>4</td> <td>4</td> <td>WHITE / Blue</td> <td>GREEN</td> <td></td> </tr> <tr> <td>5</td> <td>5</td> <td>BLUE / White</td> <td>RED</td> <td></td> </tr> <tr> <td>6</td> <td>6</td> <td>WHITE / Orange</td> <td>BLACK</td> <td></td> </tr> <tr> <td>7</td> <td>7</td> <td>NOT USED</td> <td>NOT USED</td> <td></td> </tr> <tr> <td>8</td> <td>8</td> <td>NOT USED</td> <td>NOT USED</td> <td></td> </tr> </tbody> </table>	RIGHT	LEFT	Wiring Colour Codes	SOFT WIRE	SOFT WIRE	1	1	NOT USED	NOT USED		2	2	GREEN / White	BLUE		3	3	ORANGE / White	YELLOW		4	4	WHITE / Blue	GREEN		5	5	BLUE / White	RED		6	6	WHITE / Orange	BLACK		7	7	NOT USED	NOT USED		8	8	NOT USED	NOT USED		 <p data-bbox="1230 464 1398 506">Hamilton® HARTLAND CFX</p> <p data-bbox="1208 510 1421 537">2J12 2 gang RJ12 Outlet Unshielded 6 wire</p>
RIGHT	LEFT	Wiring Colour Codes	SOFT WIRE	SOFT WIRE																																											
1	1	NOT USED	NOT USED																																												
2	2	GREEN / White	BLUE																																												
3	3	ORANGE / White	YELLOW																																												
4	4	WHITE / Blue	GREEN																																												
5	5	BLUE / White	RED																																												
6	6	WHITE / Orange	BLACK																																												
7	7	NOT USED	NOT USED																																												
8	8	NOT USED	NOT USED																																												

Primary Range	Hartland CFX
Insert Type	2 gang RJ12 Outlet - Unshielded
Plate Finish	Hartland CFX Polished Brass
Insert Colour	Black
EAN13 Barcode	5017504241568
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips
Minimum Wall Box Depth	35mm
Switched Poles	N/A
IP Rating	IP2XD
Contact Gap Minimum	N/A
Earth Terminal Capacity 1	5 x 1mm ²
Earth Terminal Capacity 2	4 x 1.5mm ²
Earth Terminal Capacity 3	3 x 2.5mm ²
Earth Terminal Capacity 4	1 x 4mm ² Multi-strand
Earth Terminal Capacity 5	1 x 6mm ²
Product Class 1	Must be earthed (ref BS7671 415.2.1)
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
EuroFix Additional Notes	Can be used as either RJ11 (4 wires) or RJ12 (6 wires)
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445

All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes.	Correct as at 16 October 2018 12:36 PM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ
 T: +44 (0)1747 860088 F: +44 (0)1179 710414
 E: info@hamilton-litestat.com www.hamilton-litestat.com
 Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB
 Registered in London No. 941624 VAT Registration No. 222 6607 84



CERT. No. FM1238