




## 72CUS13W

### Hartland CFX Satin Brass 1 gang 13A Unswitched Socket White

Item Image	Wiring	Dimensions
		
Primary Range	Hartland CFX	
Insert Type	1 gang 13A Unswitched Socket	
Plate Finish	Hartland CFX Satin Brass	
Insert Colour	White	
EAN13 Barcode	5017504009519	
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm	
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips	
Minimum Wall Box Depth	35mm	
Switched Poles	None	
Current Rating	13 Amp	
Voltage	220/250V AC	
Maximum Load	13 Amp	
Mains Frequency	50Hz	
IP Rating	IP2XD	
Contact Gap Minimum	None	
Terminal Capacity 1	3 x 2.5mm <sup>2</sup>	
Terminal Capacity 2	3 x 4mm <sup>2</sup>	
Terminal Capacity 3	2 x 6mm <sup>2</sup> Multi-Strand	
Terminal Capacity 4	1 x 10mm <sup>2</sup>	
Earth Terminal Capacity 1	3 x 2.5mm <sup>2</sup>	
Earth Terminal Capacity 2	3 x 4mm <sup>2</sup>	
Earth Terminal Capacity 3	2 x 6mm <sup>2</sup> Multi-strand	
Earth Terminal Capacity 4	1 x 10mm <sup>2</sup>	
Product Class 1	Must be earthed	
Ambient Operating Temperature	-5° to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS 1363-2	
Additional Notes	Shuttered: Yes	
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes.	Correct as at 16 October 2018 12:37 PM E&OE

# Hamilton<sup>®</sup>

making connections beautifully

SL

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio