




## 72SPNSB-B

### Hartland Satin Brass 1 gang 13A Double Pole Fused Spur and Neon Satin Brass/Black

Item Image	Wiring	Dimensions
		

Primary Range	Hartland
Insert Type	1 gang 13A Double Pole Fused Spur + Neon
Plate Finish	Hartland Box Satin Brass
Insert Colour	Satin Brass/Black
EAN13 Barcode	5017503222926
Dimensions (Nominal)	Single: Height = 88.0mm Width = 88.0mm Depth = 5.0mm
Weight	140 GR
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = N/A
Minimum Wall Box Depth	35mm
Switched Poles	Double
Current Rating	13 Amp
Voltage	220/250V AC
Maximum Load	13 Amp
Mains Frequency	50Hz
IP Rating	IP2XD
Contact Gap Minimum	3mm
Terminal Capacity 1	3 x 2.5mm <sup>2</sup>
Terminal Capacity 2	2 x 4mm <sup>2</sup> Multi Strand
Terminal Capacity 3	1 x 6mm <sup>2</sup>
Earth Terminal Capacity 1	6 x 1mm <sup>2</sup>
Earth Terminal Capacity 2	5 x 1.5mm <sup>2</sup>
Earth Terminal Capacity 3	3 x 2.5mm <sup>2</sup>
Earth Terminal Capacity 4	2 x 4mm <sup>2</sup> Multi-strand
Earth Terminal Capacity 5	1 x 6mm <sup>2</sup>
Product Class 1	Must be earthed
Ambient Operating Temperature	-5° to +40°C
Recommended Location	Internal Use Only
Maximum Installation Altitude	2000m
Standard/Approval	BS 1363-4
Patents and Trademarks	Hartland is a Registered Trade Mark No. 2344778

<p>All products listed conform to current British or European standard and the product information is correct at the time of going to press.</p>	<p>All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.</p>	<p>It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.</p>
<p>Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.</p>	<p>Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.</p>	<p>Correct as at 16 October 2018 12:55 PM E&amp;OE</p>