Hamilton

making connections beautifully

		nart Lighting Control & Multi-room Audio
	743XLEDITB100	
Hartland Satin Ste	el 3g 100W LED 2 Way Push On/Off Rotary	Dimmer Satin Steel
Item Image	Wiring	Dimensions
		Hemilton HARLAND HARLEDITB LEDITB100 2 Way Dimmer
Primary Range	Hartland	
nsert Type	3 gang 100W LED Trailing/Leading Edge Push On/Off Rotary 2 Way Switching Dimmer	
late Finish	Hartland Box Satin Steel	
isert Colour	Satin Steel	
AN13 Barcode	5017504079321	
imensions (Nominal)	Double: Height = 88.0mm Width = 144.5mm Depth = 5.0mm	
ixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = N/A	
linimum Wall Box Depth	35mm	
Vattage	5-70W Per Gang	
witched Poles	Single	
urrent Rating	0.3A Per Gang	
oltage	230V-240V	
laximum Load	5-70W Per Gang	
lains Frequency	50Hz	
P Rating	IP2XD	
erminal Capacity 1	2X1mm ²	
erminal Capacity 2	2X1.5mm ²	
arth Terminal Capacity 1	5X1mm ²	
arth Terminal Capacity 2	4X1.5mm ²	
arth Terminal Capacity 3	3X2.5mm ²	
arth Terminal Capacity 4	1X4mm ² Multi-Strand	
arth Terminal Capacity 5	1X6mm ²	
roduct Class 1	Face plate muct be earthed	
mbient Operating Temperature	-5°C to +40°C	
ecommended Location	Internal Use Only	
laximum Installation Altitude	2000m	
tandard/Approval	BS EN 60669-2-1	
dditional Notes	Trailing Edge & Leading Edge Dimmer	
atents and Trademarks	Hartland is a Registered Trade Mark No. 2344778	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 16 October 2018 12:56 E8

SL