



78C3XLEDITB100

Hartland CFX Black Nickel 3g 100W LED 2 Way Push On/Off Rotary Dimmer Black Nickel

Item Image	Wiring	Dimensions
		
Primary Range	Hartland CFX	
Insert Type	3 gang 100W LED Trailing/Leading Edge Push On/Off Rotary 2 Way Switching Dimmer	
Plate Finish	Hartland CFX Black Nickel	
Insert Colour	Black Nickel	
EAN13 Barcode	5017504079628	
Dimensions (Nominal)	Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm	
Fixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = CFX Clips	
Minimum Wall Box Depth	35mm	
Wattage	5-70W Per Gang	
Switched Poles	Single	
Current Rating	0.3A Per Gang	
Voltage	230V-240V	
Maximum Load	5-70W Per Gang	
Mains Frequency	50Hz	
IP Rating	IP2XD	
Terminal Capacity 1	2X1mm ²	
Terminal Capacity 2	2X1.5mm ²	
Earth Terminal Capacity 1	5X1mm ²	
Earth Terminal Capacity 2	4X1.5mm ²	
Earth Terminal Capacity 3	3X2.5mm ²	
Earth Terminal Capacity 4	1X4mm ² Multi-Strand	
Earth Terminal Capacity 5	1X6mm ²	
Product Class 1	Face plate must be earthed	
Ambient Operating Temperature	-5°C to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS EN 60669-2-1	
Additional Notes	Trailing Edge & Leading Edge Dimmer	
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 16 October 2018 12:39 PM E&OE