## Hamilton

## making connections beautifully

	Wiring Accessories • Circuit Protection • Sn	hare 25 hars control of hard contribution
	<u>79CEURO4</u>	
Hartland CFX EuroFix Antique	Brass Double Plate complete with 4 EuroFix	Apertures 100x50mm and Grid
Item Image	Wiring	Dimensions
		Hemilton HARTLAND CFX EURO4 Double plate with 4 x EuroFix cut out
rimary Range	EuroFix	
sert Type	4 Gang EuroFix 100x50mm Apertured Plate with Grid	
late Finish	Hartland CFX EuroFix Antique Brass	
sert Colour	No Insert Colour	
AN13 Barcode	5017504299187	
imensions (Nominal)	Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm	
ixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = CFX Clips	
linimum Wall Box Depth	As Per Inserts	
witched Poles	N/A	
P Rating	N/A	
ontact Gap Minimum	N/A	
arth Terminal Capacity 1	5 x 1mm2	
arth Terminal Capacity 2	4x1.5mm2	
arth Terminal Capacity 3	3 x 2.5mm2	
arth Terminal Capacity 4	1 x 4mm2 Multi-strand	
arth Terminal Capacity 5	1 x 6mm2	
roduct Class 1	Face plate must be earthed	
ecommended Location	Internal Use Only	
aximum Installation Altitude	2000m	
dditional Notes	See EuroFix for a full range of inserts. Plates must be Earthed via the Earth Tag.	
atents and Trademarks	EuroFix is a Registered Trade Mark No. 2560270	-
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 15 October 2018 09:02 Er

SL