




## 79J12B

### Hartland Antique Brass 1 gang RJ12 Outlet - Unshielded Black

Item Image	Wiring	Dimensions																		
	 <table border="1" data-bbox="808 646 966 730"> <thead> <tr> <th>RIGHT RJ11/12 Wiring colour codes</th> <th>LEFT RJ11/12 Wiring colour codes</th> </tr> </thead> <tbody> <tr> <td>1 NOT USED</td> <td>NOT USED</td> </tr> <tr> <td>2 GREEN / White</td> <td>BLUE</td> </tr> <tr> <td>3 ORANGE / White</td> <td>YELLOW</td> </tr> <tr> <td>4 BLUE / Blue</td> <td>GREEN</td> </tr> <tr> <td>5 WHITE / White</td> <td>RED</td> </tr> <tr> <td>6 WHITE / Orange</td> <td>BLACK</td> </tr> <tr> <td>7 NOT USED</td> <td>NOT USED</td> </tr> <tr> <td>8 NOT USED</td> <td>NOT USED</td> </tr> </tbody> </table>	RIGHT RJ11/12 Wiring colour codes	LEFT RJ11/12 Wiring colour codes	1 NOT USED	NOT USED	2 GREEN / White	BLUE	3 ORANGE / White	YELLOW	4 BLUE / Blue	GREEN	5 WHITE / White	RED	6 WHITE / Orange	BLACK	7 NOT USED	NOT USED	8 NOT USED	NOT USED	 <p><b>Hamilton®</b> HARTLAND J12 1 gang RJ12 Outlet Unshielded 6 wire</p>
RIGHT RJ11/12 Wiring colour codes	LEFT RJ11/12 Wiring colour codes																			
1 NOT USED	NOT USED																			
2 GREEN / White	BLUE																			
3 ORANGE / White	YELLOW																			
4 BLUE / Blue	GREEN																			
5 WHITE / White	RED																			
6 WHITE / Orange	BLACK																			
7 NOT USED	NOT USED																			
8 NOT USED	NOT USED																			
Primary Range	Hartland																			
Insert Type	1 gang RJ12 Outlet - Unshielded																			
Plate Finish	Hartland Box Antique Brass																			
Insert Colour	Black																			
EAN13 Barcode	5028690291718																			
Dimensions (Nominal)	Single: Height = 88.0mm Width = 88.0mm Depth = 5.0mm																			
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = N/A																			
Minimum Wall Box Depth	35mm																			
Switched Poles	N/A																			
IP Rating	IP2XD																			
Contact Gap Minimum	N/A																			
Earth Terminal Capacity 1	5 x 1mm <sup>2</sup>																			
Earth Terminal Capacity 2	4 x 1.5mm <sup>2</sup>																			
Earth Terminal Capacity 3	3 x 2.5mm <sup>2</sup>																			
Earth Terminal Capacity 4	1 x 4mm <sup>2</sup> Multi-strand																			
Earth Terminal Capacity 5	1 x 6mm <sup>2</sup>																			
Product Class 1	Must be earthed (ref BS7671 415.2.1)																			
Ambient Operating Temperature	-5° to +40°C																			
Recommended Location	Internal Use Only																			
Maximum Installation Altitude	2000m																			
EuroFix Additional Notes	Can be used as either RJ11 (4 wires) or RJ12 (6 wires)																			
Patents and Trademarks	Hartland is a Registered Trade Mark No. 2344778																			
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.																		
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 16 October 2018 12:59 PM E&OE																		

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ  
 T: +44 (0)1747 860088 F: +44 (0)1179 710414  
 E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB  
 Registered in London No. 941624 VAT Registration No. 222 6607 84

