


7EBCSS2USBULTBL-B

Hartland CFX Etrium Bronze 2 gang 13A Double Pole Switched Socket with 2 USB Ultra Outlets 2x2.4A Black/Black

Item Image	Wiring	Dimensions
Primary Range	Hartland CFX	
Insert Type	2 gang 13A Double Pole Switched Socket with 2 USB Outlets 2x2.4A (4.8A Total)	
Plate Finish	Hartland CFX Etrium Bronze	
Insert Colour	Black/Black	
EAN13 Barcode	5017504090180	
Commodity Code	85363010	
Luckins TSI	405688496	
Dimensions (Nominal)	Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm	
Fixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = CFX Clips	
Minimum Wall Box Depth	35mm	
Switched Poles	Double	
Current Rating	13 Amp, USB = 2.4A	
Voltage	180/250V AC	
Maximum Load	13 Amp, USB = 2.4A	
Mains Frequency	50/60Hz	
IP Rating	IP2XD	
Contact Gap Minimum	3mm	
Terminal Capacity 1	3 x 2.5mm ²	
Terminal Capacity 2	3 x 4mm ²	
Terminal Capacity 3	2 x 6mm ² Multi-Strand	
Earth Terminal Capacity 1	3 x 2.5mm ²	
Earth Terminal Capacity 2	3 x 4mm ²	
Earth Terminal Capacity 3	2 x 6mm ² Multi-strand	
Product Class 1	Must be earthed	
Ambient Operating Temperature	-15°C to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS 1363 + BS 5733 + EN 60950-1	
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 03 July 2019 07:23 AM E&OE