

## 7G27SS2USBULTBC-QG

Hartland G2 Bright Chrome 2 gang 13A Double Pole Switched Socket with 2 USB Ultra Outlets 2x2.4A Bright Chrome/Quartz Grey

Item Image	Wiring	Dimensions
Primary Range		Hartland G2
Insert Type		2 gang 13A Double Pole Switched Socket with 2 USB Outlets 2x2.4A (4.8A Total)
Plate Finish		Hartland G2 Bright Chrome
Insert Colour		Bright Chrome/Quartz Grey
EAN13 Barcode		5051164001674
Commodity Code		85363010
Luckins TSI		407519000
Dimensions (Nominal)		Double: Height = 87.4mm Width = 144.4mm Depth = 4.65mm
Fixing Hole Centres		Box Fixing = 120.6mm
Minimum Wall Box Depth		35mm
Switched Poles		Double
Current Rating		13 Amp, USB = 2.4A
Voltage		180/250V AC
Maximum Load		13 Amp, USB = 2.4A
Mains Frequency		50/60Hz
IP Rating		IP2XD
Contact Gap Minimum		3mm
Terminal Capacity 1		3 x 2.5mm <sup>2</sup>
Terminal Capacity 2		3 x 4mm <sup>2</sup>
Terminal Capacity 3		2 x 6mm <sup>2</sup> Multi-Strand
Earth Terminal Capacity 1		3 x 2.5mm <sup>2</sup>
Earth Terminal Capacity 2		3 x 4mm <sup>2</sup>
Earth Terminal Capacity 3		2 x 6mm <sup>2</sup> Multi-strand
Product Class 1		Must be earthed
Ambient Operating Temperature		-15°C to +40°C
Recommended Location		Internal Use Only
Maximum Installation Altitude		2000m
Standard/Approval		BS 1363 + BS 5733 + EN 60950-1
Patents and Trademarks		Hartland G2 is a Registered Trade Mark No UK00003388376
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 14 August 2019 04:05 PM E&OE