Hamilton

making connections beautifully

Hortland CO Matt Place	<u>7G2MB45SS1BL-B</u>	
	45A Double Pole Rocker + Neon + 13A Switche	A Socket Red+Black/Black
Item Image	Wiring	Dimensions
		Hemilton HARTLAND G2 45SS1 Double Pole Red Rocker & Neon & 13A Switched Socket
rimary Range	Hartland G2	
sert Type	45A Double Pole Red Rocker + Neon + 13A Switched Socket	
late Finish	Hartland G2 Matt Black	
sert Colour	Red+Black/Black	
AN13 Barcode	5051164004224	
ommodity Code	85363030	
uckins TSI	407519615	
imensions (Nominal)	Double: Height = 87.4mm Width = 144.4mm Depth = 4.65mm	
xing Hole Centres	Box Fixing = 120.6mm	
inimum Wall Box Depth	35mm	
witched Poles	Double	
urrent Rating	Switch 45 Amp Socket 13 Amp	
oltage	220/250V AC	
aximum Load	Switch 45 Amp Socket 13	
ains Frequency	50Hz	
P Rating	IP2XD	
ontact Gap Minimum	3mm	
erminal Capacity 1	3 x 6mm2	
erminal Capacity 2	2 x 10mm2	
erminal Capacity 3	1 x 16mm2	
arth Terminal Capacity 1	3 x 6mm2	
arth Terminal Capacity 2	2 x 10mm2	
arth Terminal Capacity 3	1 x 16mm2	
roduct Class 1	Must be earthed	
mbient Operating Temperature	-5° to +40°C	
ecommended Location	Internal Use Only	
aximum Installation Altitude	2000m	
tandard/Approval	BS 4177	
atents and Trademarks	Hartland G2 is a Registered Trade Mark No UK00003388376	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. Therefore, we reserve the right to alter designs and dimensions without prior notice.	
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 14 August 2019 04:05 E8

7G2MB45SS1BL-B - Hartland G2 Matt Black 45A Double Pole Rocker + Neon + 13A Switched Socket Red+Black/Black

SL