



7G2RB2XLEDITB100

Hartland G2 Richmond Bronze 2g 100W LED 2 Way Push On/Off Rotary Dimmer Richmond Bronze

Item Image	Wiring	Dimensions
		
Primary Range	Hartland G2	
Insert Type	2 gang 100W LED Trailing/Leading Edge Push On/Off Rotary 2 Way Switching Dimmer	
Plate Finish	Hartland G2 Richmond Bronze	
Insert Colour	Richmond Bronze	
EAN13 Barcode	5051164003555	
Commodity Code	85365015	
Luckins TSI	407516663	
Dimensions (Nominal)	Single: Height = 87.4mm Width = 87.4mm Depth = 4.65mm	
Fixing Hole Centres	Box Fixing = 60.3mm	
Minimum Wall Box Depth	35mm	
Wattage	5-70W Per Gang	
Switched Poles	Single	
Current Rating	0.3A Per Gang	
Voltage	230V-240V	
Maximum Load	5-70W Per Gang	
Mains Frequency	50Hz	
IP Rating	IP2XD	
Terminal Capacity 1	2X1mm ²	
Terminal Capacity 2	2X1.5mm ²	
Earth Terminal Capacity 1	5X1mm ²	
Earth Terminal Capacity 2	4X1.5mm ²	
Earth Terminal Capacity 3	3X2.5mm ²	
Earth Terminal Capacity 4	1X4mm ² Multi-Strand	
Earth Terminal Capacity 5	1X6mm ²	
Product Class 1	Face plate must be earthed	
Ambient Operating Temperature	-5°C to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS EN 60669-2-1	
Additional Notes	Trailing Edge & Leading Edge Dimmer	
Patents and Trademarks	Hartland G2 is a Registered Trade Mark No UK00003388376	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 14 August 2019 04:06 PM E&OE