## Hamilton

## making connections beautifully

SL

|   | Wiring Accessories • Circuit Protection • Sn             | nart Lighting Control & Multi-room Audio                                  |  |
|---|--|---|--|
| LDRRTRB-RBB   |  |   |  |
| Linea-Duo CFX Richmond Bronze Frame/Richmond Bronze Front 1 gang 10AX Push To Make/Push to Break Retractive Rocker<br>Richmond Bronze/Black |  |   |  |
| Item Image  | Wiring   | Dimensions  |  |
|   |  | ELINE A DUO GEX<br>CEXRIT<br>Push to Make/Push to Break Retractive Rocker |  |
| Primary Range   | Linea-Duo CFX  |   |  |
| Insert Type   | 1 gang 10AX Push To Make/Push to Break Retractive Rocker | r   |  |
| Plate Finish  | Linea-Duo CFX Richmond Bronze Frame/Richmond Bronze      |   |  |
| Insert Colour   | Richmond Bronze/Black                                    |   |  |
| EAN13 Barcode   | 5017504041144  |   |  |
| Dimensions (Nominal)  | Single: Height = 86.0mm Width = 86.0mm Depth = 4.0mm     |   |  |
| Fixing Hole Centres   | Box Fixing = 60.3mm Grid Fixing = CFX Clips              |   |  |
| Minimum Wall Box Depth  | 25mm   |   |  |
| Switched Poles  | Single   |   |  |
| Current Rating  | 10AX   |   |  |
| Voltage   | 220/250V AC  |   |  |
| Maximum Load  | 10 Amp inductive   |   |  |
| Mains Frequency   | 50Hz   |   |  |
| IP Rating   | IP2XD  |   |  |
| Contact Gap Minimum   | 3mm  |   |  |
| Terminal Capacity 1   | 5 x 1mm2   |   |  |
| Terminal Capacity 2   | 4 x 1.5mm2   |   |  |
| Terminal Capacity 3   | 1 x 2.5mm2   |   |  |
| Terminal Capacity 4   | 1 x 4mm2 Multi-strand                                    |   |  |
| Terminal Capacity 5   | 1 x 6mm2   |   |  |
| Earth Terminal Capacity 1   | 5 x 1mm2   |   |  |
| Earth Terminal Capacity 2   | 4 x 1.5mm2   |   |  |
| Earth Terminal Capacity 3   | 3 x 2.5mm2   |   |  |
| Earth Terminal Capacity 4   | 1 x 4mm2 Multi-strand                                    |   |  |
| Earth Terminal Capacity 5   | 1 x 6mm2   |   |  |
| Product Class 1   | Must be earthed  |   |  |
| Ambient Operating Temperature   | -5° to +40°C   |   |  |
| Recommended Location  | Internal Use Only  |   |  |
| Maximum Installation Altitude   | 2000m  |   |  |
| Standard/Approval   | BS EN 60669-1  |   |  |
| · · ·   | I  |   |  |

# Hamilton

### making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

#### LDRRTRB-RBB

Linea-Duo CFX Richmond Bronze Frame/Richmond Bronze Front 1 gang 10AX Push To Make/Push to Break Retractive Rocker Richmond Bronze/Black

| Patents and Trademarks  | Linea is a Registered Trade Mark No 2398665<br>CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B<br>Linea-Duo CFX is a UK Registered Design Certificate No: R21 = 3021173 SS2 = 3021174 |  |
|---|--|--|
| All products listed conform to current British or<br>European standard and the product information is<br>correct at the time of going to press. | All accessories are manufactured under an accredited<br>BS EN ISO 9001 : 2015 Quality Management System.   | It is the policy of the company to improve products<br>as part of our development programme.<br>Therefore, we reserve the right to alter designs<br>and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within<br>the limitations of reproduction and printing<br>process and are not binding.                | Due to manufacturing processes we cannot<br>guarantee an exact colour match and shadings of<br>of certain finishes.  | Correct as at 15 October 2018 08:21 AM<br>E&OE   |
|   | ad, Brislington, Bristol, BS4 5NZ<br>ice 1 Rushmills, Bedford Road, Northampton NN4 7YB<br>ondon No. 941624 VAT Registration No. 222 6607 84   | Listed in STrimble LUCKINS riba product selector   |

SL