

SL

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

LRX3XTSCB-CBB

Linea-Rondo CFX Copper Bronze Frame/Copper Bronze Front 3 gang Multi-Way Touch Slave Controller Copper Bronze/Black

Linea-Rondo CFX Copper Bronze Frame/Copper Bronze Front 3 gang Multi-Way Touch Slave Controller Copper Bronze/Black			
Item Image	Wiring	Dimensions	
	Multi-Way Wiring using Slave module(s) Multi-Way Wiring using Slave module(s) List 3 Q Q Q List 3 List 3 List 4 List 4 AMASTER MODILE SLAVE MODILE SLAVE MODULE ONLY ONE MASTER MODILE IS USED PER CIRCUIT.	Hemiton LINEA RONDO CFX 3XTS Multi-WayTouch Slave Controller	
Primary Range	Linea-Rondo CFX		
Insert Type	3 gang Multi-Way Touch Slave Controller		
Plate Finish	Linea-Rondo CFX Copper Bronze Frame/Copper Bronze		
Insert Colour	Copper Bronze/Black		
EAN13 Barcode	5017504055080		
Dimensions (Nominal)	Double: Height = 91.5mm Width = 150.5mm Depth = 4.0mm		
Fixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm		
Wattage	The same as Touch Master or Ceiling Dimmer		
Switched Poles	N/A		
Current Rating	The same as Touch Master or Ceiling Dimmer		
Voltage	220/250V AC		
Maximum Load	The same as Touch Master		
Mains Frequency	50Hz		
IP Rating	IP2XD		
Contact Gap Minimum	N/A		
Terminal Capacity 1	2 x 1mm2		
Terminal Capacity 2	2 x 1.5mm2		
Earth Terminal Capacity 1	5 x 1mm2		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m		
Standard/Approval	BS EN 60669-2-1		
Additional Notes	Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When using mains voltage halogen load transformer - maximum rating is 210VA. To only be used with Touch Master Dimmers		



SL

making connections beautifully

	Wiring Accessories • Circuit Protection • Sr	mart Lighting Control & Multi-room Audio		
LRX3XTSCB-CBB				
Linea-Rondo CFX Copper Bronze Fram	ne/Copper Bronze Front 3 gang Multi-Way To	uch Slave Controller Copper Bronze/Black		
Patents and Trademarks	Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Community Trd Mark No. 002906428 Linea-Rondo CFX is a UK Registered Design Certificate No: R21=2106349 SS2=2106350			
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.		
Illustrations and diagrams are reproduced within the limitations of reproduction and printing	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of or certain finishes	Correct as at 16 October 2018 04:03 PM E&OE		

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 F: +44 (0)1179 710414 E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84











