



making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

LRXRRTEB-EBB

Linea-Rondo CFX Etrium Bronze Frame/Etrium Bronze Front 1 gang 10AX Push To Make/Push to Break Retractive Rocker Etrium Bronze/Black

| | Ethani Bronze/Black | T | |
|-------------------------------|--|---|--|
| Item Image | Wiring | Dimensions | |
| | Com L2 L1 | LINEA RONDO CFX CFXRRT Push to Make/Push to Break Retractive Rocker | |
| Primary Range | Linea-Rondo CFX | | |
| Insert Type | 1 gang 10AX Push To Make/Push to Break Retractive Rocker | | |
| Plate Finish | Linea-Rondo CFX Etrium Bronze Frame/Etrium Bronze | | |
| Insert Colour | Etrium Bronze/Black | | |
| EAN13 Barcode | 5017504058784 | | |
| Dimensions (Nominal) | Single: Height = 91.5mm Width = 91.5mm Depth = 4.0mm | | |
| Fixing Hole Centres | Box Fixing = 60.3mm Grid Fixing = CFX Clips | | |
| Minimum Wall Box Depth | 25mm | | |
| Switched Poles | Single | | |
| Current Rating | 10AX | | |
| Voltage | 220/250V AC | | |
| Maximum Load | 10 Amp inductive | | |
| Mains Frequency | 50Hz | | |
| IP Rating | IP2XD | | |
| Contact Gap Minimum | 3mm | | |
| Terminal Capacity 1 | 5 x 1mm2 | | |
| Terminal Capacity 2 | 4 x 1.5mm2 | | |
| Terminal Capacity 3 | 1 x 2.5mm2 | | |
| Terminal Capacity 4 | 1 x 4mm2 Multi-strand | | |
| Terminal Capacity 5 | 1 x 6mm2 | | |
| Earth Terminal Capacity 1 | 5 x 1mm2 | 5 x 1mm2 | |
| Earth Terminal Capacity 2 | 4 x 1.5mm2 | | |
| Earth Terminal Capacity 3 | 3 x 2.5mm2 | | |
| Earth Terminal Capacity 4 | 1 x 4mm2 Multi-strand | | |
| Earth Terminal Capacity 5 | 1 x 6mm2 | | |
| Product Class 1 | Must be earthed | | |
| Ambient Operating Temperature | -5° to +40°C | | |
| Recommended Location | Internal Use Only | | |
| Maximum Installation Altitude | 2000m | | |
| Standard/Approval | BS EN 60669-1 | | |



SL

making connections beautifully

Wiring Accessories • Circuit Protection • Smart Lighting Control & Multi-room Audio

LRXRRTEB-EBB

Linea-Rondo CFX Etrium Bronze Frame/Etrium Bronze Front 1 gang 10AX Push To Make/Push to Break Retractive Rocker Etrium Bronze/Black

| Ethan Bionzo/Black | | | |
|---|---|--|--|
| Patents and Trademarks | Linea is a Registered Trade Mark No 2398665 CFX is a Registered Trade Mark No 2398667 Patent No. GB 2383375B Community Trd Mark No. 002906428 Linea-Rondo CFX is a UK Registered Design Certificate No: R21=2106349 SS2=2106350 | | |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. | |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of | Correct as at 16 October 2018 04:09 PM E&OE | |

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 F: +44 (0)179 710414 Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB E: info@hamilton-litestat.com www.hamilton-litestat.com Registered in London No. 941624 VAT Registration No. 222 6607 84









