

Selection table

Powerpact 4 panelboards

2

| | 250A Powerboard | 250A Panelboard | 400/630A Panelboard | 800A Panelboard | 1600A panelboard |
|--|--------------------|--------------------|------------------------|--------------------|---------------------|
| Busbar short circuit withstand | 36kA, 1s | 36kA, 1s | 36kA, 1s | 50kA, 1s | 50kA, 1s |
| Number of outgoing ways | | | | | |
| 13SP inc incomer | ■ | | | | |
| 17SP inc incomer | ■ | | | | |
| 15SP (5TP) | | ■ | | | |
| 18SP (6TP) | | | ■ | ■ | |
| 21SP (7TP) | | ■ | | | |
| 27SP (9TP) | | ■ | | | |
| 36SP (12TP) | | | ■ | ■ | |
| 39SP (13TP) | | ■ | | | |
| 42SP (14TP) | | | | | ■ |
| 54SP (18TP) | | | ■ | ■ | |
| 84SP (28 TP) | | | | | □ |
| Incoming device | | | | | |
| 100A MCCB | □ | □ | | | |
| 160A MCCB | □ | □ | | | |
| 250A MCCB | □ | □ | □ | | |
| 400A MCCB | | | □ | | |
| 630A MCCB | | | □ | | |
| 800A MCCB | | | | ■ | |
| 1250A MCCB | | | | | □ |
| 1600A MCCB | | | | | □ |
| 250A fuse switch | | □ | | | |
| Incomer - field installable | ■ | ■ | ■ | ■ | ■ |
| Two incomers, mechanically interlocked | □ | | | | |
| Main incoming cable entry | | | | | |
| Top | | □ | □ | □ | □ |
| Bottom | ■ | □ | □ | □ | □ |
| Incoming metering | □ | | □ | □ | ■ |
| Outgoing metering | □ | | □ | □ | □ |
| Top/bottom extension boxes | | □ | □ | □ | |
| Side extension boxes | □ | | □ | □ | □ |
| Integrated control and distribution unit | | | □ | □ | |
| Earth leakage protection on outgoing circuits | | | □ | □ | □ |

Standard ■ Option □